

# 1.85mm Male to 3.5mm Female Bulkhead Cable FM-SR086TBJ Coax

#### FMCA100350

#### Configuration

· Connector 1: 1.85mm Male

· Connector 2: 3.5mm Female Bulkhead

Cable Type: FM-SR086TBJCoax Flex Type: Formable

#### **Features**

- Max Frequency 20 GHz
- Shielding Effectivity > 100 dB
- · 69.5% Phase Velocity
- FEP Jacket
- · 500 Mating Cycles

#### **Applications**

· General Purpose

· Laboratory Use

#### **Description**

The 1.85mm male to 3.5mm female bulkhead cable using FM-SR086TBJ coax, part number FMCA100350, from Fairview Microwave is in-stock and ships same day. This Fairview 1.85mm to 3.5mm cable assembly has a male to female gender configuration with 50 ohm formable FM-SR086TBJ coax. Fairview Microwave's formable RF cable assemblies provide an alternative to costly pre-formed semi-rigid assemblies since they are hand formable. The FMCA100350 1.85mm male to 3.5mm female cable assembly operates to 20 GHz. Our RF cable assembly with 3.5mm bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		20	GHz
VSWR			1.4:1	
Velocity of Propagation		69.5		%
RF Shielding	100			dB
Group Delay		1.43 [4.69]		ns/ft [ns/m]
Capacitance		29 [95.14]		pF/ft [pF/m]
DC Resistance Inner Conductor		65.7 [215.55]		Ohms/1000ft [Ohms/Km]
DC Resistance Outer Conductor		10.2 [33.46]		Ohms/1000ft [Ohms/Km]
Operating Voltage (AC)			250	Vrms

#### Specifications by Frequency



# 1.85mm Male to 3.5mm Female Bulkhead Cable FM-SR086TBJ Coax

## FMCA100350



Part Number Length	Longth	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
	Frequency	1000	2000	4500	9000	20000	MHz	weight (ibs)	
FMCA100350	Custom Lengths	Insertion Loss (Typ.)	0.225	0.306	0.508	0.759	1.2	dB/ft	
I WEATOOSSO	Available	111361 tio11 to33 (19p.)	0.74	1.01	1.67	2.5	3.94	dB/m	
FMCA100350-6	6 In	Insertion Loss (Typ.)	0.26	0.31	0.44	0.6	0.88	dB	0.04
FMCA100350-9	9 In	Insertion Loss (Typ.)	0.31	0.39	0.57	0.79	1.18	dB	0.045
FMCA100350-12	12 ln	Insertion Loss (Typ.)	0.37	0.47	0.7	0.98	1.48	dB	0.05
FMCA100350-18	18 ln	Insertion Loss (Typ.)	0.48	0.62	0.95	1.36	2.08	dB	0.061
FMCA100350-24	24 In	Insertion Loss (Typ.)	0.59	0.77	1.21	1.74	2.68	dB	0.071

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

Loss due to Connector 1: 0.04\*SQRT(FGHz) dB
Loss due to Connector 2: 0.1 dB
Base Weight: 0.05 pounds
Additional Weight per Inch: 0.00167 pounds

#### **Mechanical Specifications**

#### Cable Assembly

 Width/Diameter
 0.5 in [12.7 mm]

 Weight
 0.05 lbs [22.68 g]

#### Cable

Cable Type FM-SR086TBJ
Impedance 50 Ohms
Inner Conductor Type Solid
Inner Conductor Material and Plating Copper Clad Steel, Silver

Dielectric Type PTFE

Number of Shields 1
Outer Conductor 1 Material and Plating 1

Outer Conductor 1 Material and Plating

Tinned Copper Composite Braid

Jacket MaterialFEP, BlackJacket Diameter0.105 in [2.67 mm]

One Time Minimum Bend Radius 0.5 in [12.7 mm]
Repeated Minimum Bend Radius 0.787 in [19.99 mm]



## 1.85mm Male to 3.5mm Female Bulkhead Cable FM-SR086TBJ Coax

### FMCA100350

#### **Connectors**

Description	Connector 1	Connector 2			
Туре	1.85mm Male	3.5mm Female Bulkhead			
Impedance	50 Ohms	50 Ohms			
Configuration	Straight	Straight			
Mating Cycles	500	500			
Contact Material and Plating	Beryllium Copper, Gold over Nickel	Beryllium Copper, Gold over Nickel over			
		Copper			
Contact Plating Specification	50 μin minimum				
Dielectric Type	PEI	PPO			
Body Material and Plating	Beryllium Copper, Gold over Nickel	Stainless Steel, Passivated			
Body Plating Specification	50 μin minimum				
Coupling Nut Material and Plating	Passivated Stainless Steel	Stainless Steel, Passivated			
Coupling Nut Plating Specification	ASTM-A582				
Hex Size	5/16 inch				
Torque	8 in-lbs 0.9 Nm	7.1 in-lbs 0.8 Nm			

#### **Environmental Specifications**

**Operating Range Temperature** 

-55 to +105 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:




# 1.85mm Male to 3.5mm Female Bulkhead Cable FM-SR086TBJ Coax



#### FMCA100350

#### **Typical Performance Data**

#### **How to Order**



Example: FMCA100350-12 = 12 inches long cable FMCA100350-100cm = 100 cm long cable

1.85mm Male to 3.5mm Female Bulkhead Cable FM-SR086TBJ Coax from Fairview Microwave is in-stock and available to ship sameday. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 1.85mm Male to 3.5mm Female Bulkhead Cable FM-SR086TBJ Coax FMCA100350

URL: https://www.fairviewmicrowave.com/1.85mm-male-to-3.5mm-female-bulkhead-cable-fm-sr086tbj-coax-fm-ca100350-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

