

SMA Male (Plug) to BNC Female (Jack) Adapter, Commercial Grade

FMAD10073

Configuration

- SMA Male Connector 1
- · BNC Female Connector 2
- · VSWR 1.6 Max. Under 4 GHz

- 50 Ohms Impedance
- Straight Body Geometry

Applications

· Enables Between Series Connections

· General Purpose Test

Description

SMA male to BNC female adapter part number FMAD10073 from Fairview Microwave is in-stock and ships same day. This Fairview SMA to BNC adapter has a male to female gender configuration. FMAD10073 SMA male to BNC female adapter. The SMA connector mates mechanically with commercially available 3.5mm and 2.92mm (K) connectors.

RF adapters can be used to enable connections between two connector types that would otherwise not mate. Certain RF adapter configurations can also be used to protect connectors on expensive equipment where the number of connect and disconnect cycles is high. An RF, microwave, or millimeter wave adapter is connected to the equipment and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Fairview Microwave also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

	Description	Minimum	Typical	Maximum	Units
Impedance			50		Ohms

Mechanical Specifications

Size

 Length
 1.00 in [25.40 mm]

 Width
 0.50 in [12.70 mm]

 Height
 0.50 in [12.70 mm]

 Weight
 0.02 lbs [9.07 g]

Description	Connector 1	Connector 2
Polarity	Standard	Standard

Material Specifications

	Connector 1		Connector 2	
Description	Material	Plating	Material	Plating
Туре	SMA Male		BNC Female	
Contact		Gold		Gold
Insulation	POM		POM	



SMA Male (Plug) to BNC Female (Jack) Adapter, Commercial Grade



FMAD10073

Material Specifications

	Connector 1		Connector 2	
Description	Material	Plating	Material	Plating
Outer Conductor	Brass	Nickel	Brass	Nickel
Body	Brass	Nickel	Brass	Nickel
Coupling Nut	Brass	Nickel		

Compliance Certifications (see product page for current document)

SMA Male (Plug) to BNC Female (Jack) Adapter, Commercial Grade from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: SMA Male (Plug) to BNC Female (Jack) Adapter, Commercial Grade FMAD10073

URL: https://www.fairviewmicrowave.com/product/rf-adapters/sma-male-to-bnc-female-adapter-fmad10073.html

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

