



# **TNC Male to TNC Female Bulkhead Cable LMR-100 Coax**

The TNC male to TNC female bulkhead cable using LMR-100 coax, part number FMC00053, from Fairview Microwave is in-stock and ships same day. This Fairview TNC to TNC cable assembly has a male to female gender configuration with 50 ohm flexible LMR-100A coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00053 TNC male to TNC female cable assembly operates to 5.8 GHz. Our RF cable assembly with TNC bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

# **Electrical Specifications**

N	1in	T	ур	Max	ι	Inits
[	DC			5.8		GHz
				1.4:1		
		6	6			%
(	90					dB
		1.54	[5.05]		ns/f	t [ns/m]
		30.8 [101.05]			pF/ft [pF/m]	
		0.077	[0.25]		uH/fl	t [uH/m]
DC Resistance Inner Conductor		81 [265.75]			Ω/1000ft [Ω/Km]	
nductor		9.5 [3	31.17]		Ω/100	Oft [Ω/Km]
				2,000	\	/rms
		DC 90	DC 90 1.54 30.8 [: 0.077 nductor 81 [2	DC  66  90  1.54 [5.05]  30.8 [101.05  0.077 [0.25]  nductor  81 [265.75]	DC 5.8  1.4:1  66  90  1.54 [5.05]  30.8 [101.05]  0.077 [0.25]  nductor 81 [265.75]  anductor 9.5 [31.17]	DC 5.8  1.4:1  66  90  1.54 [5.05] ns/fi  30.8 [101.05] pF/fi  0.077 [0.25] uH/fi  nductor 81 [265.75] Ω/100  anductor 9.5 [31.17] Ω/100

## **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.11	0.16	0.24	0.39	0.64	dB/ft
	0.36	0.52	0.79	1.28	2.1	dB/m

**Electrical Specification Notes:** 

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as 0.1 dB for the straight connectors  $\frac{1}{2}$ 

## **Mechanical Specifications**

**Cable Assembly** 

Diameter

0.68 in [17.27 mm]



# **Configuration:**

- TNC Male
- TNC Female Bulkhead
- LMR-100A

## **Features:**

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 66% Phase Velocity
- · Double Shielded
- PVC Jacket

# **Applications:**

- General Purpose
- Laboratory Use
- Antenna Installations
- Land Mobile Radio & Other Communication Systems
- Cellular & Wi-Fi Systems

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Cable

Cable Type LMR-100A Impedance 50 Ohms Inner Conductor Type Solid

Inner Conductor Material and Plating Copper Clad Steel Dielectric Type PE

Dielectric Type Number of Shields

Shield Layer 1 Aluminum Tape
Shield Layer 2 Tinned Copper Braid
Jacket Material PVC, Black

2

Jacket Diameter 0.11 in [2.79 mm]

One Time Minimum Bend Radius

0.25 in [6.35 mm]
Repeated Minimum Bend Radius

1 in [25.4 mm]

Repeated Minimum Bend Radius 1 in [25.4 mm]
Bending Moment 0.1 lbs-ft [0.14 N-m]
Flat Plate Crush 10 lbs/in [0.18 Kg/mm]

Tensile Strength 15 lbs [6.8 Kg]

#### **Connectors**

Description	Connector 1		Connector 2
Туре	TNC Ma	ıle	TNC Female
Mount Method			Bulkhead
Specification			MIL-STD-348
Impedance	50 Ohn	าร	50 Ohms
Contact Material & Plating	Brass, G	old	Phosphor Bronze, Gold
Dielectric Type	PTFE		PTFE
Outer Cond Material & Plat	ing		Brass, Nickel
Body Material & Plating	Brass, Ni	ckel	Brass, Nickel
Coupling Nut Material & Pla	ating Brass, Ni	ckel	
Hex Size			5/8 in

Mechanical Specification Notes:

## **Environmental Specifications**

**Temperature** 

Operating Range -40 to +85 deg C Storage Range -70 to +85 deg C

**Compliance Certifications** (see product page for current document)

#### **Plotted and Other Data**

Notes:

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2019 REV 1.0 Page 2 of 4

<sup>\*</sup>All cable assemblies have a length tolerance of 1.5% or  $\pm$  3/8", whichever is greater.





#### **How to Order**

Part Number Configuration:	FMC00053	-	XX	uu	
					cm = Centimeters <blank> = Inches Length</blank>

Example: FMC00053-12 = 12 inches long cable

FMC00053-100cm = 100 cm long cable

TNC Male to TNC Female Bulkhead Cable LMR-100 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: TNC Male to TNC Female Bulkhead Cable LMR-100 Coax FMC00053

URL: https://www.fairviewmicrowave.com/tnc-male-tnc-female-cable-lmr100-coax-fmc00053-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





