

# **FMC00289-60 DATA SHEET**

## SMA Male to MMCX Jack Cable LMR-100 Coax in 60 Inch

The SMA male to MMCX jack 60 inch cable using LMR-100 coax, part number FMC00289-60, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to MMCX cable assembly has a male to jack gender configuration with 50 ohm flexible LMR-100A coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00289-60 SMA male to MMCX jack cable assembly operates to 5.8 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

## **Electrical Specifications**

Description	Mir	) T	ур	Max	ι	Jnits	
Frequency Range	DC			5.8		GHz	
VSWR				1.4:1			
Velocity of Propagation			66			%	
RF Shielding	90					dB	
Group Delay		1.54	[5.05]		ns/f	t [ns/n	n]
Capacitance		30.8 [	101.05	]	pF/f	t [pF/n	n]
Inductance		0.077	7 [0.25]		uH/f	t [uH/r	m]
DC Resistance Inner Cor	nductor	81 [2	265.75]		Ω/100	Oft [Ω/I	Km]
DC Resistance Outer Cor	nductor	9.5 [	31.17]		Ω/100	Oft [Ω/I	Km]
Jacket Spark				2,000	١	/rms	

### **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.78	1.02	1.4	2.2	3.4	dB

#### **Electrical Specification Notes:**

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB per connector.

## **Mechanical Specifications**

#### **Cable Assembly**

Length\* 60 in [152.4 cm]
Diameter 0.312 in [7.92 mm]

## Cable

Cable Type LMR-100A Impedance 50 Ohms



## **Configuration:**

- SMA Male
- MMCX Jack
- LMR-100A

## Features:

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 66% Phase Velocity
- Double Shielded
- PVC Jacket

## **Applications:**

- General Purpose
- · Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields Shield Layer 1 Shield Layer 2 Jacket Material

Jacket Material

Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius

Bending Moment Flat Plate Crush Tensile Strength Solid

Copper Clad Steel

PE 2

Aluminum Tape Tinned Copper Braid

PVC, Black

0.11 in [2.79 mm]

0.25 in [6.35 mm] 1 in [25.4 mm] 0.1 lbs-ft [0.14 N-m] 10 lbs/in [0.18 Kg/mm]

15 lbs [6.8 Kg]

#### **Connectors**

Description	Connector 1	Connector 2
Туре	SMA Male	MMCX Jack
Specification	MIL-STD-348A	BS EN 122340
Impedance	50 Ohms	50 Ohms
Contact Material & Plating	Brass, Gold	Beryllium Copper, Gold
Contact Plating Spec.	50 µin minimum	30 µin minimum
Dielectric Type	PTFE	PTFE
Body Material & Plating	Brass, Nickel	Brass, Gold
Body Plating Spec.	100 μin minimum	3 µin minimum
Coupling Nut Material & Pla	nting Brass, Nickel	
Coupling Nut Plating Spec.	100 μin minimum	
Hex Size	5/16 inch	
Torque	3 in-lbs 0.34 Nm	1

## Mechanical Specification Notes:

## **Environmental Specifications**

**Temperature** 

Operating Range -40 to +85 deg C Storage Range -70 to +85 deg C

**Compliance Certifications** (see product page for current document)

## **Plotted and Other Data**

Notes:

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2019 REV 1.0 Page 2 of 4

<sup>\*</sup>All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.





## **How to Order**

Part Number Configuration:	FMC00289	- xx	uu	
				cm = Centimeters <blank> = Inches Length</blank>

Example: FMC00289-12 = 12 inches long cable

FMC00289-100cm = 100 cm long cable

SMA Male to MMCX Jack Cable LMR-100 Coax in 60 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: SMA Male to MMCX Jack Cable LMR-100 Coax in 60 Inch FMC00289-60

URL: https://www.fairviewmicrowave.com/sma-male-mmcx-jack-cable-lmr100-coax-fmc00289-60-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





