

RA MMCX Plug to BNC Female Cable LMR-100 Coax in 99.2 CM

The RA MMCX plug to BNC female 99.2 cm cable using LMR-100 coax, part number FMC00318-100CM, from Fairview Microwave is in-stock and ships same day. This Fairview MMCX to BNC cable assembly has a plug to female gender configuration with 50 ohm flexible LMR-100A coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00318-100CM MMCX plug to BNC female cable assembly operates to 1 GHz. The right angle MMCX interface on the LMR-100A cable allows for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	ι	Jnits	
Frequency Range	DC			1,000		MHz	
VSWR				1.4:1			
Velocity of Propagation		(66			%	
RF Shielding	90					dB	
Group Delay		1.54	[5.05]		ns/f	t [ns/n	n]
Capacitance	30.8 [101.05]			pF/ft [pF/m]			
Inductance		0.077	7 [0.25]		uH/f	t [uH/r	m]
DC Resistance Inner Cor	nductor	81 [2	265.75]		Ω/100	Oft [Ω/	Km]
DC Resistance Outer Cor	nductor	9.5 [31.17]		Ω/100	Oft [Ω/	Km]
Jacket Spark				2,000	١	/rms	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Typ.)	0.47	0.53	0.68	0.84	1.09	dB

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

Mechanical Specifications

Cable Assembly

Length* Diameter 39.07 in [992.38 mm] 0.453 in [11.51 mm]

FMC00318-100CM DATA SHEET



Configuration:

- MMCX Plug Right Angle
- BNC Female
- LMR-100A

Features:

- Max Frequency 1 GHz
- Shielding Effectivity > 90 dB
- 66% Phase Velocity
- Double Shielded
- PVC Jacket

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Cable

Cable Type LMR-100A Impedance 50 Ohms Inner Conductor Type Solid

Inner Conductor Material and Plating Copper Clad Steel

Dielectric Type PE Number of Shields 2

Shield Layer 1 Aluminum Tape
Shield Layer 2 Tinned Copper Braid

Jacket Material PVC, Black

Jacket Diameter 0.11 in [2.79 mm]

One Time Minimum Bend Radius

Repeated Minimum Bend Radius

1 in [25.4 mm]

Bending Moment

O.1 lbs-ft [0.14 N-m]

Flat Plate Crush

10 lbs/in [0.18 Kg/mm]

Tensile Strength 15 lbs [6.8 Kg]

Connectors

Description	Connector 1	Connector 2				
Туре	MMCX Plug	BNC Female				
Specification	MIL-STD-348A	MIL-STD-348A				
Impedance	50 Ohms	50 Ohms				
Contact Material & Plating	Brass, Gold	Brass, Gold				
Contact Plating Spec.	30 µin minimum	30 µin minimum				
Dielectric Type	PTFE	PTFE				
Body Material & Plating	Brass, Gold	Brass, Nickel				
Body Plating Spec.	3 µin minimum	100 µin minimum				

Mechanical Specification Notes:

Environmental Specifications

Temperature

Operating Range -40 to +85 deg C Storage Range -70 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration: FMC00318 - xx uu | cm = Centimeters | cblank> = Inches | Length

Example: FMC00318-12 = 12 inches long cable

FMC00318-100cm = 100 cm long cable

Copyright © 2019 REV 1 Page 2 of 4

^{*}All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.





RA MMCX Plug to BNC Female Cable LMR-100 Coax in 99.2 CM from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: RA MMCX Plug to BNC Female Cable LMR-100 Coax in 99.2 CM FMC00318-100CM

> The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order

URL: https://www.fairviewmicrowave.com/ra-mmcx-plug-bnc-female-cable-lmr100-coax-fmc00318-100cm-p.aspx

to implem	ent improvements	s. Fairview	Microw	ave reserv	es the righ	nt to mak	ke such	changes	as req	uired.	Unless	s oth	erwise
stated, all	specifications are	e nominal.	Fairvie	w Microwa	ve does n	ot make	any re	presentat	ion or	warrar	ity reg	gardii	ng the
suitability	of the part descri	ibed hereir	for any	particular	purpose,	and Fair	rview M	icrowave	does i	not ass	ume a	any li	ability
arising out	t of the use of any	part or do	cument	ation.									



FMC00318-100CM DATA SHEET

