

FMC00338-12 **DATA SHEET**

MMCX Jack to BNC Male Cable RG-316 Coax in 12 Inch

The MMCX jack to BNC male 12 inch cable using RG-316 coax, part number FMC00338-12, from Fairview Microwave is in-stock and ships same day. This Fairview MMCX to BNC cable assembly has a jack to male gender configuration with 50 ohm flexible RG316 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00338-12 MMCX jack to BNC male cable assembly operates to 3 GHz.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	U	nits
Frequency Range	DC			3		GHz
VSWR				1.4:1		
Velocity of Propagation		(59			%
Capacitance		29.4	[96.46]	pF/ft	[pF/m]
Operating Voltage (AC)				250	V	'rms
Jacket Spark				2,000	V	'rms
				·		

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.1	0.25	0.5	1	3	GHz
Insertion Loss (Max.)	0.31	0.33	0.37	0.58	0.78	dB

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax used in this assembly. Insertion Loss is estimated as 0.1 dB per connector.

Mechanical Specifications

Cable Assembly

Jacket Diameter

Length* 12 in [304.8 mm] Diameter 0.571 in [14.5 mm]

Cable

Cable Type **Impedance** Inner Conductor Type Inner Conductor Material and Plating Dielectric Type Number of Shields Shield Layer 1 Jacket Material

RG316 50 Ohms Stranded Copper Clad Steel, Silver **PTFE**

Silver Plated Copper Braid FEP, Tan

0.102 in [2.59 mm]



Configuration:

- MMCX Jack
- BNC Male
- RG316

Features:

- Max Frequency 3 GHz
- 69% Phase Velocity
- FEP Jacket

Applications:

- General Purpose
- · Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Connectors

Description	Connector 1	Connector 2			
Туре	MMCX Jack	BNC Male			
Specification	BS EN 122340	MIL-STD-348A			
Impedance	50 Ohms	50 Ohms			
Contact Material & Plating	Beryllium Copper, G	ld Brass, Gold			
Contact Plating Spec.	30 µin minimum	50 µin minimum			
Dielectric Type	PTFE	PTFE			
Body Material & Plating	Brass, Gold	Brass, Nickel			
Body Plating Spec.	3 µin minimum	100 µin minimum			
Coupling Nut Material & Pla	ting	Brass, Nickel			
Coupling Nut Plating Spec.		100 µin minimum			

Environmental Specifications

Temperature

Operating Range

-55 to +155 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

• Values at 25°C, sea level.

How to Order





MMCX Jack to BNC Male Cable RG-316 Coax in 12 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: MMCX Jack to BNC Male Cable RG-316 Coax in 12 Inch FMC00338-12

The information contained in this document is accurate to the best of our knowledge and representative of the part

URL: https://www.fairviewmicrowave.com/mmcx-jack-bnc-male-cable-rg316-coax-fmc00338-12-p.aspx

to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.	described	herein.	It may be	necessar	y to ma	ke modifica	tions to the	e part a	nd/or t	ne docum	entation o	f the part	, in order
suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability	to implem	ent impr	ovements	. Fairview	/ Microw	ave reserve	es the right	to mak	e such (changes a	s required	. Unless	otherwise
	stated, all	specifica	ations are	nominal.	Fairvie	w Microway	e does not	make	any rep	resentatio	n or warr	anty rega	rding the
arising out of the use of any part or documentation.	suitability	of the pa	art descril	bed hereir	for an	y particular	purpose, a	and Fair	view Mi	crowave c	loes not a	ssume ar	y liability
	arising ou	t of the u	se of any	part or do	ocument	tation.							





