

# FMC00370-24 DATA SHEET

## N Male to RA BNC Male Cable RG-58 Coax in 24 Inch

The type N male to RA BNC male 24 inch cable using RG-58 coax, part number FMC00370-24, from Fairview Microwave is in-stock and ships same day. This Fairview type N to BNC cable assembly has a male to male gender configuration with 50 ohm flexible RG58C/U coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00370-24 type N male to BNC male cable assembly operates to 3 GHz. The right angle BNC interface on the RG58C/U cable allows for easier connections in tight spaces.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

## **Electrical Specifications**

Description	Min	Т	ур	Max	ι	Inits
Frequency Range	DC			3		GHz
VSWR				1.4:1		
Velocity of Propagation		6	6			%
Capacitance	30.8 [101.05]				pF/f	t [pF/m]

## **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.1	0.25	0.5	1	3	GHz
Insertion Loss (Max.)	0.4	0.44	0.5	0.7	1.06	dB

### **Electrical Specification Notes:**

The Insertion Loss data above is based on the performance specifications of the coax used in this assembly. Insertion Loss is estimated as 0.1 dB for the N Male connector and 0.2 dB for the BNC Male connector.

### **Mechanical Specifications**

### **Cable Assembly**

Length\* 24 in [609.6 mm]
Diameter 0.78 in [19.81 mm]

#### Cable

Cable Type RG58C/U 50 Ohms **Impedance** Inner Conductor Type Stranded Inner Conductor Material and Plating Copper, Tin Dielectric Type PΕ Number of Shields Shield Layer 1 Tinned Copper Braid Jacket Material PVC, Black Jacket Diameter 0.195 in [4.95 mm]



## **Configuration:**

- N Male
- BNC Male Right Angle
- RG58C/U

## **Features:**

- Max Frequency 3 GHz
- 66% Phase Velocity
- PVC Jacket

## **Applications:**

- General Purpose
- · Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





### **Connectors**

Description	Connect	or 1	Connector 2		
Туре	N Mal	е	BNC Male		
Specification	MIL-STD-	348	MIL-STD-348A		
Impedance	50 Ohr	ns	50 Ohms		
Contact Material & Plating	Brass, G	old	Brass, Gold		
Contact Plating Spec.	MIL-G-45	204	30µ in. minimum		
Dielectric Type	PTFE		Teflon		
Body Material & Plating	Brass, Nickel		Brass, Nickel		
Body Plating Spec.	QQ-N-290		100µ in. minimum		
Coupling Nut Material & Pla	iting		Brass, Nickel		
Coupling Nut Plating Spec.			100µ in. minimum		

## **Environmental Specifications**

**Temperature** 

Operating Range

-40 to +80 deg C

**Compliance Certifications** (see product page for current document)

## **Plotted and Other Data**

Notes:

• Values at 25°C, sea level.

### **How to Order**

Part Number Configuration:

FMC00370 - xx uu

cm = Centimeters
<br/>
<br/>
<br/>
clank> = Inches

Length

Example: FMC00370-12 = 12 inches long cable
FMC00370-100cm = 100 cm long cable





N Male to RA BNC Male Cable RG-58 Coax in 24 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: N Male to RA BNC Male Cable RG-58 Coax in 24 Inch FMC00370-

URL: https://www.fairviewmicrowave.com/n-male-ra-bnc-male-cable-rg58-coax-fmc00370-24-p.aspx







