

FMC1732315-36 DATA SHEET

RA MCX Male to SMA Male Cable RG-316 Coax in 36 Inch

The RA MCX male to SMA male 36 inch cable using RG-316 coax, part number FMC1732315-36, from Fairview Microwave is in-stock and ships same day. This Fairview MCX to SMA cable assembly has a male to male gender configuration with 50 ohm flexible RG-316 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC1732315-36 MCX male to SMA male cable assembly operates to 3 GHz. The right angle MCX interface on the RG-316 cable allows for easier connections in tight spaces.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

| Description | Min | Т | ур | Max | ι | Inits |
|-------------------------|-----|-------|-------|-------|------|----------|
| Frequency Range | DC | | | 3 | | GHz |
| VSWR | | | | 1.5:1 | | |
| Velocity of Propagation | | - | 70 | | | % |
| Capacitance | | 32 [1 | 04.99 |] | pF/f | t [pF/m] |

Performance by Frequency

| Description | F1 | F2 F3 | | F4 | F5 | Units | | |
|-----------------------|------|-------|------|------|------|-------|--|--|
| Frequency | 0.25 | 0.5 | 1 | 2.5 | 3 | GHz | | |
| Insertion Loss (Typ.) | 0.78 | 0.99 | 1.44 | 1.89 | 2.04 | dB | | |

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.3dB of connector loss.

Mechanical Specifications

Cable Assembly

Length* 36 in [914.4 mm]
Weight 0.044 lbs [19.96 g]

Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1
Jacket Material
Jacket Diameter

RG-316 50 Ohms Solid Copper, Silver

PTFE 1

Silver Plated Copper Braid

FEP, Tan

0.098 in [2.49 mm]



Configuration:

- MCX Male Right Angle
- SMA Male
- RG-316

Features:

- Max Frequency 3 GHz
- 70% Phase Velocity
- FEP Jacket

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com

sales@fairviewmicrowave.com





Connectors

| Description | Connector 1 | Connector 2 | | | | | |
|----------------------------|-------------|------------------|--|--|--|--|--|
| Туре | MCX Male | SMA Male | | | | | |
| Impedance | 50 Ohms | 50 Ohms | | | | | |
| Contact Material & Plating | Brass, Gold | Brass, Gold | | | | | |
| Dielectric Type | Teflon | Teflon | | | | | |
| Body Material & Plating | Brass, Gold | Brass, Gold | | | | | |
| Hex Size | | 5/16 inch | | | | | |
| Torque | | 5 in-lbs 0.57 Nm | | | | | |
| | | | | | | | |

Mechanical Specification Notes:

Environmental Specifications

Temperature

Operating Range


-40 to +60 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Typical Performance Data



How to Order

Part Number Configuration: FMC1732315 - xx uu | cm = Centimeters | cblank> = Inches

Example: FMC1732315-12 = 12 inches long cable

FMC1732315-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Length

^{*}All cable assemblies have a length tolerance of 1.5% or \pm 3/8", whichever is greater.






RA MCX Male to SMA Male Cable RG-316 Coax in 36 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.


Click the following link to obtain additional part information: RA MCX Male to SMA Male Cable RG-316 Coax in 36 Inch FMC1732315-36

URL: https://www.fairviewmicrowave.com/ra-mcx-male-sma-male-cable-rg-316-coax-fmc1732315-36-p.aspx









| How To Order | | Part # Ext. | | Length In Inches | | Part # Ext. Lengt | | Length | ength In Centimeters | | |
|---|--------------------|-----------------|-------------------------------|---|---------------|-------------------|--------|--------|----------------------|-----|--|
| Part Number Configuration | | <u>Examples</u> | -12 | | 12" | | -25cm | 2 | 25cm | | |
| FMC zzzzzzz - xx uu | | FMC000-100 | -24 | | 24" | | -50cm | 5 | 50cm | | |
| _ cm = Centimeters < Blank > = Inches | | FMC000-100cm | MC000-100cm -36 -48 -60 | | 36" | | -75cm | 7 | 75cm | | |
| | cm = Centimeters | | | | 48" | | -100cm | 1 | 100cm | | |
| | < Blank > = Inches | | | | 60" | | -125cm | 1 | 125cm | | |
| Length | | | -xx | | Custom Length | | -xxcm | | Custom Length | | |
| FAIRVIEW MICROWAVE INC. ALLEN, TX 75013 WWW.FAIRVIEWMICROWAVE.COM | | | • | NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm]. | | | | | | | |
| RA MCX Male to SMA Male Cable RG-316 Coax in 36 | | | 1 | DWG NO FMC1732315-12 | | | | | CAGE CODE 3FKR5 | | |
| Inch | | | CAD FILE | 091914 | SHEET | | SCAI | LE N/A | SIZE A | 150 | |