

VITA 67.3 SMPS Female to SMPS Female Cable FM-P047HF Coax

Committee of the control of the cont

FMCA100377

Configuration

Connector 1: SMPS Female
Connector 2: SMPS Female
Cable Type: FM-P047HF
Coax Flex Type: High Flex

Features

- Max Frequency 40 GHz
- Shielding Effectivity > 90 dB
- 70% Phase Velocity
- · Double Shielded
- · FEP Jacket

JACKET OUTER SHIELD INNER SHIELD O.056 Ø [1.4] DIELECTRIC SOLID CENTER CONDUCTOR

Applications

· General Purpose

· Laboratory Use

Description

The SMPS female to SMPS female cable using FM-P047HF coax, part number FMCA100377, from Fairview Microwave is in-stock and ships same day. This Fairview SMPS to SMPS cable assembly has a female to female gender configuration with 50 ohm high flex FM-P047HF coax. The FMCA100377 SMPS female to SMPS female cable assembly operates to 40 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		40	GHz
VSWR			1.4:1	
Velocity of Propagation		70		%
RF Shielding	90			dB
Capacitance		29 [95.14]		pF/ft [pF/m]

Specifications by Frequency



VITA 67.3 SMPS Female to SMPS Female Cable FM-P047HF Coax

Common Co

FMCA100377

Part Number	Length	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
		Frequency	2500	5000	10000	20000	40000	MHz	
FMCA100377	Custom Lengths	Insertion Loss (Typ.)	0.557	0.808	1.177	1.784	2.774	dB/ft	
TWICATOUS //	Available	ilisertion Loss (Typ.)	1.83	2.66	3.87	5.86	9.11	dB/m	
FMCA100377-6	6 In	Insertion Loss (Typ.)	0.48	0.61	0.79	1.1	1.59	dB	0.004
FMCA100377-9	9 In	Insertion Loss (Typ.)	0.62	0.81	1.09	1.54	2.29	dB	0.005
FMCA100377-12	12 ln	Insertion Loss (Typ.)	0.76	1.01	1.38	1.99	2.98	dB	0.006
FMCA100377-18	18 ln	Insertion Loss (Typ.)	1.04	1.42	1.97	2.88	4.37	dB	0.008
FMCA100377-24	24 In	Insertion Loss (Typ.)	1.32	1.82	2.56	3.77	5.75	dB	0.01

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

Loss due to Connector 1:

0.1 dB

Loss due to Connector 2:

0.1 dB

Base Weight:

0.0058 pounds

Additional Weight per Inch:

0.00034 pounds

Mechanical Specifications

Cable Assembly

 Width/Diameter
 0.5 in [12.7 mm]

 Weight
 0.006 lbs [2.72 g]

Cable

Cable TypeFM-P047HFImpedance50 OhmsInner Conductor TypeSolidInner Conductor Material and PlatingCopper, Silver

Dielectric Type PTFE
Number of Shields 2

Shield Layer 1 Silver Plated Copper Tape
Shield Layer 2 Silver Plated Copper Braid
Jacket Material FEP, Blue

Jacket Diameter0.06 in [1.52 mm]Repeated Minimum Bend Radius0.1 in [2.54 mm]

Connectors

Description	Connector 1	Connector 2		
Туре	SMPS Female	SMPS Female		
Impedance	50 Ohms	50 Ohms		
Configuration	Straight	Straight		
Contact Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold		
Dielectric Type	PTFE	PTFE		
Outer Conductor Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold		
Body Material and Plating	Passivated Stainless Steel	Passivated Stainless Steel		



VITA 67.3 SMPS Female to SMPS Female Cable FM-P047HF Coax



FMCA100377

Environmental Specifications

Operating Range Temperature

-65 to +165 deg C


Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Typical Performance Data

How to Order



Example: FMCA100377-12 = 12 inches long cable

FMCA100377-100cm = 100 cm long cable

VITA 67.3 SMPS Female to SMPS Female Cable FM-P047HF Coax from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: VITA 67.3 SMPS Female to SMPS Female Cable FM-P047HF Coax FMCA100377

URL: https://www.fairviewmicrowave.com/vita-67.3-smps-female-to-smps-female-cable-fm-p047hf-coax-fmca100377-p. aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

