




FMCA10072

Configuration

Connector 1: SMA MaleConnector 2: N MaleCable Type: RG-316Coax Flex Type: Flexible

Features

- · Max Frequency 3 GHz
- · FEP Jacket



Applications

· General Purpose

· Laboratory Use

Description

The SMA male to type N male cable using RG-316 coax, part number FMCA10072, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to type N cable assembly has a male to male gender configuration with 50 ohm flexible RG-316 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA10072 SMA male to type N male cable assembly operates to 3 GHz.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		3	GHz
VSWR			1.4:1	
Capacitance		32 [104.99]		pF/ft [pF/m]

Specifications by Frequency





FMCA10072

Part Number	Length	Description	F1	F2	F3	F4	F5	Units	Weight (lbs)
		Frequency	100	250	500	1000	3000	MHz	
FMCA10072	Custom Lengths	Insertion Loss (Typ.)	0.11	0.16	0.24	0.38	0.58	dB/ft	
	Available		0.37	0.53	0.79	1.25	1.91	dB/m	
FMCA10072-12	12 Inch	Insertion Loss (Typ.)	0.46	0.51	0.59	0.73	0.93	dB	0.062
FMCA10072-24	24 Inch	Insertion Loss (Typ.)	0.57	0.67	0.83	1.11	1.51	dB	0.071
FMCA10072-36	36 Inch	Insertion Loss (Typ.)	0.68	0.83	1.07	1.49	2.09	dB	0.08
FMCA10072-48	48 Inch	Insertion Loss (Typ.)	0.79	0.99	1.31	1.87	2.67	dB	0.089
FMCA10072-72	72 Inch	Insertion Loss (Typ.)	1.01	1.31	1.78	2.63	3.83	dB	0.107

The insertion loss data for the base model does not include loss due to the connectors. Each length includes insertion loss due to the connectors.

Loss due to Connector 1: 0.25 dB Loss due to Connector 2: 0.1 dB Base Weight: 0.062 pounds Additional Weight per Inch: 0.32917 pounds

Mechanical Specifications

Cable Assembly

Width/Diameter 0.5 in [12.7 mm] Weight 0.062 lbs [28.12 g]

Cable

Cable Type RG-316 Impedance 50 Ohms Inner Conductor Type Stranded

Inner Conductor Material and Plating Copper Clad Steel, Silver

Dielectric Type **PTFE** Number of Shields

Shield Layer 1 Silver Plated Copper Braid

Jacket Material FEP, Tan

Jacket Diameter 0.098 in [2.49 mm]





FMCA10072

Connectors

Description	Connector 1	Connector 2
Туре	SMA Male	N Male
Impedance	50 Ohms	50 Ohms
Configuration	Straight	Straight
Contact Material and Plating	Brass, Gold	Beryllium Copper, Gold
Contact Plating Specification	15 µin minimum	
Dielectric Type	PTFE	PTFE
Body Material and Plating	Brass, Nickel	Brass, Nickel
Body Plating Specification	200 μin minimum	
Coupling Nut Material and Plating	Brass, Nickel	Brass, Nickel
Coupling Nut Plating Specification	200 μin minimum	

Environmental Specifications

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:






FMCA10072

Typical Performance Data

How to Order



Example: FMCA10072-12 = 12 inches long cable

FMCA10072-100cm = 100 cm long cable

SMA Male to N Male Cable RG-316 Coax from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: SMA Male to N Male Cable RG-316 Coax FMCA10072

URL: https://www.fairviewmicrowave.com/sma-male-to-n-male-cable-rg-316-coax-fmca10072-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

