

FMCA1074/0002 DATA SHEET

Low Loss SMA Male to SMA Male Cable LMR-195 Coax with Times Microwave Components

The SMA male to SMA male cable using LMR-195 coax, part number FMCA1074/0002, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to SMA cable assembly has a male to male gender configuration with 50 ohm flexible LMR-195 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA1074/0002 SMA male to SMA male cable assembly operates to 5.8 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description		Min	Typ Max		Units		
Frequency Range		DC			5.8		GHz
VSWR					1.4:1		
Velocity of Propagation			8	30			%
RF Shielding		90					dB
Group Delay			1.27	[4.17]		ns/f	t [ns/m]
Capacitance			25.4	[83.33]		pF/fl	t [pF/m]
Inductance		0.064 [0.21]		uH/ft [uH/m]			
DC Resistance Inner Conductor		7.6 [24.93]		Ω/1000ft [Ω/Km]			
DC Resistance Outer Conductor		4.9 [16.08]		Ω/1000ft [Ω/Km]			
Jacket Spark					3,000	١	/rms

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.057	0.081	0.116	0.19	0.299	dB/ft
	0.19	0.27	0.38	0.62	0.98	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as $0.1\ dB$ per connector.

Mechanical Specifications

Cable Assembly

Weight 0.063 lbs [28.58 g]

Cable

Cable Type LMR-195
Impedance 50 Ohms
Inner Conductor Type Solid
Inner Conductor Material and Plating Copper



Configuration:

- SMA Male
- SMA Male
- LMR-195

Features:

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 80% Phase Velocity
- Double Shielded
- PE Jacket

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com

sales@fairviewmicrowave.com





Dielectric Type PE (F) Number of Shields 2

Shield Layer 1 Aluminum Tape
Shield Layer 2 Tinned Copper Braid
Jacket Material PE, Black

Jacket Diameter 0.195 in [4.95 mm]

One Time Minimum Bend Radius

Repeated Minimum Bend Radius

2 in [50.8 mm]

Bending Moment

0.2 lbs-ft [0.27 N-m]

Flat Plate Crush

15 lbs/in [0.27 Kg/mm]

Tensile Strength 40 lbs [18.14 Kg]

Connectors

Description	Connecto	r 1	Connecto	r 2	
Туре	SMA Male	Э	SMA Mal	е	
Impedance	50 Ohms	5	50 Ohm	S	
Contact Material & Plating	Brass, Gol	d	Brass, Go	ld	
Contact Plating Spec.	ASTM B48	8	ASTM B488		
Dielectric Type	PTFE		PTFE		
Body Material & Plating	Passivated Stainle	ess Steel	Passivated Stainl	ess Ste	el
Coupling Nut Material & Pla	iting Passivated Stainle	ess Steel	Passivated Stainl	ess Ste	el
Hex Size	5/16 Incl	า	5/16 Inc	:h	

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:

FMCA1074/0002 - xx

cm = Centimeters
<black> = Inches
Length

FMCA1074/0002-100cm = 100 cm long cable

Example: FMCA1074/0002-12 = 12 inches long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020

REV 1.0 Page 2 of 4





Low Loss SMA Male to SMA Male Cable LMR-195 Coax with Times Microwave Components from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low Loss SMA Male to SMA Male Cable LMR-195 Coax with Times Microwave Components FMCA1074/0002

URL: https://www.fairviewmicrowave.com/low-loss-sma-male-to-sma-male-cable-lmr-195-coax-with-times-microwave-components-fmca1074-0002-p.aspx



301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689



