

## FMCA1443-18 DATA SHEET

# Snap-On RA MMBX Plug to TNC Female Bulkhead Cable RG174 Coax in 18 Inch

Fairview Microwave's MMBX cable assemblies are part of our full line of RF interconnects available for same-day shipping. These MMBX cable assemblies are designed for test applications or connection of your MMBX system components. With a high frequency range up to 3 GHz, this family of MMBX cables can also be used to connect your panels to PCB's with between series options like MMBX-to-SMA, MMBX-to-N or MMBX-to-TNC assemblies. There are hundreds of possible cable assembly configurations to choose from, all available same day.

This MMBX cable assembly datasheet PDF contains specifications, CAD drawing and dimensions that are shown below. Fairview Microwave not only has many MMBX cable assembly options, but also a wide selection of RF, microwave and millimeter wave cable assemblies which allows RF designers to customize their configurations to whatever is required. Whether the need is to provide an I/O for a board design or simply create a custom cable assembly configuration, Fairview Microwave has the right cable assemblies for the job. Fairview can also expertly build your custom RF cable assemblies for you and ship same day.

## **Electrical Specifications**

Description	Min	Тур	Max	Units
Frequency Range	DC		3	GHz
VSWR			1.4:1	
Return Loss		-15.5	6	dB
Velocity of Propagation		66		%
Capacitance		31.1 [102	2.03]	pF/ft [pF/m]

## Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Max.)	0.29	0.33	0.41	0.53	0.68	dB

## **Mechanical Specifications**

## **Cable Assembly**

Length\* 18 in [457.2 mm]
Diameter 0.689 in [17.5 mm]

### Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1
Jacket Material
Jacket Diameter

RG174 50 Ohms Stranded Copper Clad Steel, Silver PE 1

Tinned Copper Braid PVC, Black

0.11 in [2.79 mm]



## **Configuration:**

- Snap-OnMMBX Plug Right Angle
- TNC Female Bulkhead
- RG174

## **Features:**

- Max Frequency 3 GHz
- 66% Phase Velocity
- PVC Jacket
- Max. Operating Frequency of 3 GHz
- Snap-On mating
- Low Profile Right Angle Configurations
- SMA Bulkhead, N Bulkhead and TNC Bulkhead Between-Series Configurations

## **Applications:**

- General Purpose
- Laboratory Use
- General Purpose MMBX Test
- PCB Testing
- Low Profile MMBX Cable Jumpers
- PCB-to-Panel Connection

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





#### **Connectors**

Description	Connector 1	Connector 2		
Туре	MMBX Plug	TNC Female		
Mount Method		Bulkhead		
Specification		MIL-STD-348A		
Impedance	50 Ohms	50 Ohms		
Connection Method	Snap-On			
Mating Cycles	100			
Contact Material & Plating	Beryllium Copper, G	Gold Brass, Gold		
Contact Plating Spec.		30 µin minimum		
Dielectric Type	PTFE	PTFE		
Outer Cond Material & Plat	ing Brass, Gold			
Body Material & Plating	Brass, Gold	Brass, Nickel		
Body Plating Spec.		100 µin minimum		

#### **Environmental Specifications**

**Temperature** 


Operating Range -40 to +80 deg C

**Compliance Certifications** (see product page for current document)

## Plotted and Other Data

Notes:

#### **How to Order**



Snap-On RA MMBX Plug to TNC Female Bulkhead Cable RG174 Coax in 18 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Snap-On RA MMBX Plug to TNC Female Bulkhead Cable RG174 Coax in 18 Inch FMCA1443-18

URL: https://www.fairviewmicrowave.com/ra-mmbx-plug-tnc-female-cable-rg174-coax-fmca1443-18-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





