

Low Loss N Male to N Female Bulkhead Cable LMR-240 Coax in 150 CM with Times Microwave components

The type N male to type N female bulkhead 150 cm cable using LMR-240 coax, part number FMCA1937-150CM, from Fairview Microwave is in-stock and ships same day. This Fairview type N to type N cable assembly has a male to female gender configuration with 50 ohm flexible LMR-240 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA1937-150CM type N male to type N female cable assembly operates to 5.8 GHz. Our RF cable assembly with type N bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Typ Max		Units			
Frequency Range	DC			5.8		GHz	
VSWR				1.4:1			
Velocity of Propagation		8	34			%	
RF Shielding	90					dB	
Group Delay		1.21	[3.97]		ns/f	t [ns/m	<u>1]</u>
Capacitance		24.2	[79.4]		pF/f	t [pF/n	<u>n]</u>
Inductance		0.06	[0.2]		uH/f	t [uH/n	n]
DC Resistance Inner Cor	nductor	3.2	[10.5]		Ω/100	Oft [Ω/k	(m)
DC Resistance Outer Cor	nductor	3.89	[12.76]		Ω/100	Oft [Ω/k	(m]
Jacket Spark				5,000	\	/rms	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units	
Frequency	0.25	0.5	1	2.5	5.8	GHz	
Insertion Loss (Typ.)	0.39	0.47	0.59	0.83	1.2	dB	

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB per connector.

Mechanical Specifications

Cable Assembly

Length* Diameter 59.05 in [149.99 cm] 0.89 in [22.61 mm]

FMCA1937-150CM DATA SHEET



Configuration:

- N Male
- · N Female Bulkhead
- LMR-240

Features:

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 84% Phase Velocity
- · Double Shielded
- PE Jacket

Applications:

- General Purpose
- · Laboratory Use
- Antenna Installations
- Land Mobile Radio & Other Communication Systems
- Cellular & Wi-Fi Systems

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com



FMCA1937-150CM **DATA SHEET**

Cable

Cable Type LMR-240 **Impedance** 50 Ohms Inner Conductor Type Solid Inner Conductor Material and Plating Copper Dielectric Type PE (F) Number of Shields

Shield Layer 1 Aluminum Tape Shield Layer 2 Tinned Copper Braid Jacket Material PE, Black

Jacket Diameter 0.24 in [6.1 mm]

One Time Minimum Bend Radius 0.75 in [19.05 mm] 2.5 in [63.5 mm] Repeated Minimum Bend Radius Bending Moment 0.25 lbs-ft [0.34 N-m] Flat Plate Crush 20 lbs/in [0.36 Kg/mm] Tensile Strength 80 lbs [36.29 Kg]

Connectors

Description	Connector 1	Connector 2			
Туре	N Male	N Female			
Mount Method		Bulkhead			
Specification	MIL-STD-348	MIL-STD-348			
Impedance	50 Ohms	50 Ohms			
Contact Material & Plating	Brass, Gold	Beryllium Copper, Gold			
Dielectric Type	PTFE	PTFE			
Outer Cond Material & Plating		Brass, Tri-Metal			
Body Material & Plating	Brass, Tri-Metal	Brass, Tri-Metal			
Coupling Nut Material & Plating	ling Nut Material & Plating Brass, Tri-Metal				

Mechanical Specification Notes:

Environmental Specifications Temperature

Operating Range

-40 to +85 deg C Storage Range -70 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

FMCA1937 - xx Part Number Configuration: uu cm = Centimeters

dank> = Inches - Length

Example: FMCA1937-12 = 12 inches long cable

FMCA1937-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

REV 1 Page 2 of 4 Copyright © 2019

^{*}All cable assemblies have a length tolerance of 1.5% or $\pm 3/8$ ", whichever is greater.





Low Loss N Male to N Female Bulkhead Cable LMR-240 Coax in 150 CM with Times Microwave components from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low Loss N Male to N Female Bulkhead Cable LMR-240 Coax in 150 CM with Times Microwave components FMCA1937-150CM

The information contained in this document is accurate to the best of our knowledge and representative of the part

URL: https://www.fairviewmicrowave.com/n-male-n-female-cable-lmr240-coax-fmca1937-p.aspx

	nerein. It may be								
	ent improvements				-		-		
	specifications are								
	of the part descril				purpose, and	Fairview M	icrowave doe	s not assume	any liability
arising ou	t of the use of any	part or do	cument	ation.					



FMCA1937-150CM DATA SHEET

