

FMCA1941-200CM DATA SHEET

Low Loss N Male to N Male Cable LMR-240 Coax in 200 cm

The type N male to type N male 200 cm cable using LMR-240 coax, part number FMCA1941-200CM, from Fairview Microwave is in-stock and ships same day. This Fairview type N to type N cable assembly has a male to male gender configuration with 50 ohm flexible LMR-240 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA1941-200CM type N male to type N male cable assembly operates to 5.8 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description		Min	Т	ур	Max	ι	Jnits	
Frequency Range		DC			5.8		GHz	
VSWR					1.4:1			
Velocity of Propagation			8	34			%	
RF Shielding		90					dB	
Group Delay			1.21	[3.97]		ns/f	t [ns/n	<u>n]</u>
Capacitance			24.2	[79.4]		pF/f	t [pF/n	n]
Inductance			0.06	[0.2]		uH/f	t [uH/r	n]
DC Resistance Inner Conductor			3.2	[10.5]		Ω/100	Oft [Ω/I	Km]
DC Resistance Outer Conductor		3.89	[12.76]		Ω/100	Oft [Ω/I	Km]	
Jacket Spark					5,000	\	/rms	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Max.)	0.46	0.53	0.59	1.05	1.54	dB

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax used in this assembly. Insertion Loss is estimated as 0.1 dB per connector.

Mechanical Specifications

Cable Assembly

Length* 78.74 in [200 cm]
Diameter 0.827 in [21.01 mm]

Cable

Cable Type LMR-240 Impedance 50 Ohms



Configuration:

- N Male
- N Male
- LMR-240

Features:

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 84% Phase Velocity
- Double Shielded
- PE Jacket

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields

Shield Layer 1 Shield Layer 2 Jacket Material

Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius

Bending Moment Flat Plate Crush Tensile Strength Solid Copper PE (F)

> Aluminum Tape Tinned Copper Braid

PE, Black

0.24 in [6.1 mm]

0.75 in [19.05 mm] 2.5 in [63.5 mm] 0.25 lbs-ft [0.34 N-m]

20 lbs/in [0.36 Kg/mm] 80 lbs [36.29 Kg]

Connectors

Description	Connector 1	Connector 2		
Туре	N Male	N Male		
Specification	MIL-STD-348A	MIL-STD-348A		
Impedance	50 Ohms	50 Ohms		
Contact Material & Plating	Brass, Gold	Brass, Gold		
Contact Plating Spec.	30 µin minimum	30 µin minimum		
Dielectric Type	PTFE	PTFE		
Body Material & Plating	Brass, Nickel	Brass, Nickel		
Body Plating Spec.	100 μin minimum	100 μin minimum		
Coupling Nut Material & Pla	iting Brass, Nickel	Brass, Nickel		
Coupling Nut Plating Spec.	100 µin minimum	100 µin minimum		
Dielectric Type Body Material & Plating Body Plating Spec. Coupling Nut Material & Plating	PTFE Brass, Nickel 100 µin minimum iting Brass, Nickel	PTFE Brass, Nickel 100 µin minimum Brass, Nickel		

Environmental Specifications

Temperature

Operating Range

-40 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

• Values at 25°C, sea level.

How to Order

Part Number Configuration:

Example: FMCA1941-12 = 12 inches long cable

FMCA1941-100cm = 100 cm long cable





Low Loss N Male to N Male Cable LMR-240 Coax in 200 cm from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low Loss N Male to N Male Cable LMR-240 Coax in 200 cm FMCA1941-200CM

URL: https://www.fairviewmicrowave.com/low-loss-n-male-n-male-cable-lmr240-coax-fmca1941-200cm-p.aspx





FMCA1941-200CM DATA SHEET

