

## FMCA2134-24 DATA SHEET

# RA SMA Male to N Female Bulkhead Cable FM-SR086TBJ Coax in 24 Inch

The RA SMA male to type N female bulkhead 24 inch cable using FM-SR086TBJ coax, part number FMCA2134-24, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to type N cable assembly has a male to female gender configuration with 50 ohm formable FM-SR086TBJ coax. Fairview Microwave's formable RF cable assemblies provide an alternative to costly pre-formed semirigid assemblies since they are hand formable. The FMCA2134-24 SMA male to type N female cable assembly operates to 10 GHz. The right angle SMA interface on the FM-SR086TBJ cable allows for easier connections in tight spaces. Our RF cable assembly with type N bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

## **Electrical Specifications**

Description	Min	Т	ур	Max	ι	Jnits
Frequency Range	DC			10		GHz
VSWR				1.4:1		
Velocity of Propagation		6	9.5			%
RF Shielding	100					dB
Group Delay		1.43	[4.69]		ns/f	t [ns/m]
Capacitance		29 [9	95.14]		pF/f	t [pF/m]
DC Resistance Inner Cor	nductor	65.7 [	215.55		Ω/100	0ft [Ω/Km]
DC Resistance Outer Cor	nductor	10.2	[33.46]		Ω/100	Oft [Ω/Km]

#### **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.5	1	2.5	5	10	GHz
Insertion Loss (Typ.)	0.6	0.75	0.993	1.398	1.923	dB

#### **Electrical Specification Notes:**

The Insertion Loss includes an estimated insertion loss of 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

## **Mechanical Specifications**

## **Cable Assembly**

Length\* 24 in [609.6 mm] Diameter 0.866 in [22 mm]

#### Cable

Cable Type FM-SR086TBJ Impedance 50 Ohms



## **Configuration:**

- SMA Male Right Angle
- N Female Bulkhead
- FM-SR086TBJ

## **Features:**

- Max Frequency 10 GHz
- Shielding Effectivity > 100 dB
- 69.5% Phase Velocity
- FEP Jacket
- Dimensionally and electrically the same as standard, solid outer conductor semi-rigid coax
- Cable may be formed by hand and does not require special tools to bend
- May be formed more than once without damaging the outer conductor
- High RF Shielding >100 dB
- 100% Hi-pot and continuity tested
- 100% VSWR tested to max frequency of assembly
- Standard and custom lengths ship the same day

## **Applications:**

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type

Outer Conductor Material and Plating

Jacket Material

Jacket Diameter

Solid

Copper Clad Steel, Silver

**PTFE** 

Tinned Copper Composite Braid

FEP, Black

0.105 in [2.67 mm]

One Time Minimum Bend Radius Repeated Minimum Bend Radius 0.5 in [12.7 mm] 0.787 in [19.99 mm]

#### **Connectors**

Description	Connector	1 Connect	tor 2
Туре	SMA Male	N Fem	ale
Mount Method		Bulkhe	ad
Impedance	50 Ohms	50 Ohi	ms
Contact Material & Plating	Brass, Gold over N	NickelPhosphor Bronze,	Gold over Nic
Contact Plating Spec.	0.2 µin minimu	ım	
Dielectric Type	PTFE	PTFE	
Body Material & Plating	Brass, Gold over N	Nickel Brass, N	ickel
Body Plating Spec.	0.1 µin minimu	ım	
Coupling Nut Material & Pla	nting Passivated Stainles	s Steel	
Hex Size	5/16 inch		
Torque	8 in-lbs 0.9 N	lm	

Mechanical Specification Notes:

# Compliance Certifications (see product page for current document)

## Plotted and Other Data

Notes:

Values at 25°C, sea level.

## **How to Order**

Part Number Configuration:

FMCA2134 - xx uu | cm = Centimeters | cblank> = Inches | Length

Example: FMCA2134-12 = 12 inches long cable

FMCA2134-100cm = 100 cm long cable

<sup>\*</sup>All cable assemblies have a length tolerance of 1.5% or  $\pm$  3/8", whichever is greater.





RA SMA Male to N Female Bulkhead Cable FM-SR086TBJ Coax in 24 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: RA SMA Male to N Female Bulkhead Cable FM-SR086TBJ Coax in 24 Inch FMCA2134-24

URL: https://www.fairviewmicrowave.com/ra-sma-male-n-female-cable-fm-sr086tbj-coax-fmca2134-24-p.aspx







