

Low PIM RA 4.3-10 Male to RA N Male Cable TFT-402 Coax in 100 CM Using Times Microwave Components

The RA 4.3-10 male to RA type N male 100 cm cable using TFT-402 coax, part number FMCA2449-100CM, from Fairview Microwave is in-stock and ships same day. This Fairview 4.3-10 to type N cable assembly has a male to male gender configuration with 50 ohm flexible TFT-402 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. Our low PIM design offers excellent passive intermodulation performance with PIM levels better than -160 dBc. The FMCA2449-100CM 4.3-10 male to type N male cable assembly operates to 5.8 GHz. The right angle 4.3-10 and right angle type N interfaces on the TFT-402 cable allow for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than -80 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	ι	Inits		
Frequency Range	DC			5.8		GHz		
VSWR				1.4:1				
Velocity of Propagation		7	76			%		
RF Shielding	-80					dB		
Passive Intermodulation			-160		dBc			
Capacitance		26.7 [87.6]		pF/ft [pF/m]				
DC Resistance Inner Conductor			8.5 [27.89]		Ω/1000ft [Ω/Km]			
DC Resistance Outer Conductor			5.6 [18.37]			$\Omega/1000$ ft [$\Omega/$ Km]		

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.33	0.43	0.56	0.83	1.22	dB

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1*SQRT(FGHz) dB for the 4.3-10 connector and 0.1 dB for the N connector.

Mechanical Specifications

Cable Assembly

Length* Diameter 39.37 in [100 cm] 0.86 in [21.84 mm]

FMCA2449-100CM DATA SHEET



Configuration:

- 4.3-10 Male Right Angle
- N Male Right Angle
- TFT-402

Features:

- Max Frequency 5.8 GHz
- Low PIM: -160 dBc Max
- Shielding Effectivity > -80 dB
- 76% Phase Velocity
- · Double Shielded
- FEP Jacket

Applications:

- General Purpose
- Laboratory Use
- Low PIM Applications
- Indoor and Outdoor Use
- Plenum Rated Applications

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Cable

Cable Type TFT-402 Impedance 50 Ohms Inner Conductor Type Solid

Inner Conductor Material and Plating Copper, Silver

Dielectric Type PTFE Number of Shields

Shield Layer 1 Silver Plated Copper Braid Shield Layer 2 Tinned Copper Braid

Jacket Material FEP, Blue

Jacket Diameter 0.16 in [4.06 mm]

One Time Minimum Bend Radius 0.75 in [19.05 mm]

Connectors

Description	Connector 1	Connector 2
Туре	4.3-10 Male	N Male
Impedance	50 Ohms	50 Ohms
Mating Cycles	500	
Contact Material & Plating	Brass, Silver	Brass, Silver
Contact Plating Spec.	200 μin	5 μm
Dielectric Type	PTFE	PTFE
Body Material & Plating	Brass, Tri-Metal	Brass, Tri-Metal
Body Plating Spec.	80 μin	3 µm
Coupling Nut Material & Pla	ting Brass, Tri-Metal	Brass, Tri-Metal
Coupling Nut Plating Spec.	80 μin	3 µm
Torque	44 in-lbs 4.97 Nr	n 10 in-lbs 1.13 Nm

Environmental Specifications

Temperature

-40 to +85 deg C Operating Range

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration: FMCA2449 - xx uu cm = Centimeters

lank> = Inches - Length

Example: FMCA2449-12 = 12 inches long cable

FMCA2449-100cm = 100 cm long cable





Low PIM RA 4.3-10 Male to RA N Male Cable TFT-402 Coax in 100 CM Using Times Microwave Components from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low PIM RA 4.3-10 Male to RA N Male Cable TFT-402 Coax in 100 CM Using Times Microwave Components FMCA2449-100CM

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order

URL: https://www.fairviewmicrowave.com/low-pim-ra-4.3-10-male-ra-n-male-cable-tft-402-coax-fmca2449-100cm-p. aspx

to implem	ent improvements	. Fairview	Microw	ave reserve	s the righ	it to mak	e such	changes	as req	uired.	Unless	otherwi	se
stated, all	specifications are	nominal.	Fairvie	w Microwav	e does no	ot make	any rep	resentat	ion or	warrar	nty reg	arding tl	ıe
suitability	of the part descril	bed hereir	for any	/ particular	purpose,	and Fair	view M	icrowave	does i	not ass	ume a	ny liabili	ty.
arising ou	t of the use of any	part or do	cument	ation.									





