

## FMCA2608/WH-120

## 12G SDI 75 Ohm HD-BNC Male to 75 Ohm 1.0/2.3 Male Cable 75 Ohm 4855R-WH Coax in **120 Inch**

The 75 ohm HD-BNC male to 75 ohm 1.0/2.3 male 120 inch cable using 75 ohm 4855R-WH coax, part number FMCA2608/WH-120, from Fairview Microwave is instock and ships same day. This Fairview HD-BNC to 1.0/2.3 cable assembly has a male to male gender configuration with 75 ohm flexible Belden 4855R-WH coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA2608/WH-120 HD-BNC male to 1.0/2.3 male cable assembly operates to 12 GHz and enables 12Gb/s data transfer rates for high resolution uncompressed video signal transmission. These products offer 4K and Ultra-HD quality signals that meet SMPTE Standard 2082-1.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

## **Electrical Specifications**

| Description                   | Min | T            | ур     | Max             | ι    | Inits    |
|-------------------------------|-----|--------------|--------|-----------------|------|----------|
| Frequency Range               | DC  |              |        | 12              |      | GHz      |
| VSWR                          |     |              |        | 1.5:1           |      |          |
| Velocity of Propagation       |     | 8            | 32     |                 |      | %        |
| Group Delay                   |     | 1.2 [        | [3.94] |                 | ns/f | t [ns/m] |
| Capacitance                   |     | 16.3 [53.48] |        | pF/ft [pF/m]    |      |          |
| Inductance                    |     | 0.107 [0.35] |        | uH/ft [uH/m]    |      |          |
| DC Resistance Inner Conductor |     | 19.7 [64.63] |        | Ω/1000ft [Ω/Km] |      |          |
| DC Resistance Outer Conductor |     | 3.9 [12.8]   |        | Ω/1000ft [Ω/Km] |      |          |
| Operating Voltage (AC)        |     |              |        | 300             | \    | /rms     |

#### **Performance by Frequency**

| Description           | F1   | F2   | F3   | F4   | F5   | Units |
|-----------------------|------|------|------|------|------|-------|
| Frequency             | 0.5  | 1    | 2.5  | 5    | 12   | GHz   |
| Insertion Loss (Typ.) | 0.95 | 1.28 | 1.92 | 2.69 | 4.32 | dB    |

#### **Electrical Specification Notes:**

The Insertion Loss data above is based on the performance specifications of the coax and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB per connector.

## **Mechanical Specifications**

#### **Cable Assembly**

Length\* 120 in [304.8 cm] Weight 0.3 lbs [136.08 g]

## Cable

Cable Type Impedance Belden 4855R-WH 75 Ohms

# **DATA SHEET**



## **Configuration:**

- HD-BNC Male
- 1.0/2.3 Male
- Belden 4855R-WH

## Features:

- Max Frequency 12 GHz
- 82% Phase Velocity
- PVC Jacket
- Meets SMPTE ST 2082-1
- Backwards Compatible with
- 12Gb/s Transmission
- Cost Effective

## **Applications:**

- General Purpose
- Laboratory Use
- 12G-SDI, Video, and Broadband **UHDTV**
- Broadband Internet Delivery
- Broadcast A/V
- 4K/8K Video Equipment
- Medical Equipment Requiring High Speed Video
- HD Cameras

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type

Number of Shields

Shield Layer 1 Shield Layer 2

Jacket Material

Jacket Diameter

Solid

Copper, Silver

HDPE

1

Aluminum Polyester

Tinned Copper

PVC, White

0.159 in [4.04 mm]

#### **Connectors**

| Description                   | Connector 1     | Connector 2     |  |  |
|-------------------------------|-----------------|-----------------|--|--|
| Туре                          | HD-BNC Male     | 1.0/2.3 Male    |  |  |
| Impedance                     | 75 Ohms         | 75 Ohms         |  |  |
| Contact Material & Plating    | Brass, Gold     | Brass, Gold     |  |  |
| Contact Plating Spec.         | 10 µin minimum  | 10 µin minimum  |  |  |
| Dielectric Type               | PTFE            | PTFE            |  |  |
| Outer Cond Material & Plating | Brass, Nickel   | Brass, Gold     |  |  |
| Outer Cond Plating Spec.      | 100 µin minimum | 3 µin minimum   |  |  |
| Body Material & Plating       | Brass, Nickel   | Brass, Nickel   |  |  |
| Body Plating Spec.            | 100 µin minimum | 100 μin minimum |  |  |
|                               |                 |                 |  |  |

## **Environmental Specifications**

**Temperature** 

Operating Range

-30 to +75 deg C

## **Compliance Certifications** (see product page for current document)

#### **Plotted and Other Data**

Notes:

Values at 25°C, sea level.

## **How to Order**

Part Number Configuration:

FMCA2608/WH - XX

cm = Centimeters <br/>
<br/>
dlank> = Inches

- Length

Example: FMCA2608/WH-12 = 12 inches long cable

FMCA2608/WH-100cm = 100 cm long cable

uu





12G SDI 75 Ohm HD-BNC Male to 75 Ohm 1.0/2.3 Male Cable 75 Ohm 4855R-WH Coax in 120 Inch from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: 12G SDI 75 Ohm HD-BNC Male to 75 Ohm 1.0/2.3 Male Cable 75 Ohm 4855R-WH Coax in 120 Inch FMCA2608/WH-120

URL: https://www.fairviewmicrowave.com/12g-sdi-75-ohm-hd-bnc-male-to-75-ohm-1.0-2.3-male-cable-75-ohm-4855r-wh-coax-in-120-inch-fmca2608-wh-120-p.aspx





## FMCA2608/WH-120 DATA SHEET

