



2.4mm Male to 2.4mm Female Bulkhead Cable Tinned Copper RG405 Type .086 Coax

The 2.4mm male to 2.4mm female bulkhead cable using Tinned Copper RG405 type .086 coax, part number FMCA3051, from Fairview Microwave is in-stock and ships same day. This Fairview 2.4mm to 2.4mm cable assembly has a male to female gender configuration with 50 ohm semi-rigid FM-SR086CUTN-STR coax. Fairview Microwave's semi-rigid RF cable assemblies are ideal for high performance applications and can be formed, using proper tooling, to the routing pattern required. The FMCA3051 2.4mm male to 2.4mm female cable assembly operates to 40 GHz. Our RF cable assembly with 2.4mm bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	DC		40	GHz
VSWR			1.5:1	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	2.5	5	10	20	40	GHz
Insertion Loss (Typ.)	0.316	0.477	0.8	1.2	2.4	dB/ft
	1.04	1.56	2.62	3.94	7.87	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as 0.1 dB per connector.

Mechanical Specifications

Cable Assembly

Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1

One Time Minimum Bend Radius

FM-SR086CUTN-STR 50 Ohms Solid Copper Clad Steel, Silver PTFE 1 Tinned Copper

0.05 in [1.27 mm]



Configuration:

- 2.4mm Male
- 2.4mm Female Bulkhead
- FM-SR086CUTN-STR

Features:

• Max Frequency 40 GHz

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Connectors

Description	Connector 1	Connector 2	_
Туре	2.4mm Male	2.4mm Female	•
Mount Method		Bulkhead	-
Specification		IEEE-STD-P287	-
Impedance	50 Ohms	50 Ohms	_
Mating Cycles	500		_
Contact Material & Plating	Beryllium Copper, Gold over Ni	ckelBeryllium Copper, Gold o	over Nickel
Contact Plating Spec.	MIL-G-45204	50 µin minimum	
Dielectric Type	PPO	PEI	-
Body Material & Plating	Passivated Stainless Steel	Passivated Stainless Steel	-
Body Plating Spec.	ASTM-A380	SAE-AMS-2700	-
Coupling Nut Material & Pla	ting Passivated Stainless Steel		-
Coupling Nut Plating Spec.	ASTM-A380		
Hex Size	5/16 inch		_
Torque	8 in-lbs 0.9 Nm		

Mechanical Specification Notes:

Maximum length using the straight semi rigid coax is 5ft. For lenghts greater than 5ft, please contact us

Environmental Specifications

Temperature

Operating Range -55 to +125 deg C


Compliance Certifications (see product page for current document)



Notes:

How to Order

Part Number Configuration:



Example: FMCA3051-12 = 12 inches long cable

FMCA3051-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





2.4mm Male to 2.4mm Female Bulkhead Cable Tinned Copper RG405 Type .086 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: 2.4mm Male to 2.4mm Female Bulkhead Cable Tinned Copper RG405 Type .086 Coax FMCA3051

URL: https://www.fairviewmicrowave.com/2.4mm-male-to-2.4mm-female-bulkhead-cable-tinned-copper-rg405-type-.086-coax-fmca3051-p.aspx







