

N Male to RA N Male Cable Tinned Copper RG405 Type .086 Coax in 150 CM Length

The type N male to RA type N male 150 cm cable using Tinned Copper RG405 type .086 coax, part number FMCA3055-150CM, from Fairview Microwave is instock and ships same day. This Fairview type N to type N cable assembly has a male to male gender configuration with 50 ohm semi-rigid FM-SR086CUTN-STR coax. Fairview Microwave's semi-rigid RF cable assemblies are ideal for high performance applications and can be formed, using proper tooling, to the routing pattern required. The FMCA3055-150CM type N male to type N male cable assembly operates to 11 GHz. The right angle type N interface on the FM-SR086CUTN-STR cable allows for easier connections in tight spaces.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	T	ур	Max	Units
Frequency Range	DC			11	GHz
VSWR				1.5:1	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	1	2.5	5	11		GHz
Insertion Loss (Typ.)	1.39	1.86	2.65	4.44		dB

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

Mechanical Specifications

Cable Assembly

Length* 59.06 in [150.01 cm] Weight 0.198 lbs [89.81 g]

Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1

One Time Minimum Bend Radius

FM-SR086CUTN-STR 50 Ohms

Solid

Copper Clad Steel, Silver

PTFE 1

Tinned Copper

0.05 in [1.27 mm]

FMCA3055-150CM DATA SHEET



Configuration:

- N Male
- N Male Right Angle
- FM-SR086CUTN-STR

Features:

• Max Frequency 11 GHz

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Connectors

Description	Connector 1	N Male 50 Ohms Brass, Gold	
Туре	N Male		
Impedance	50 Ohms		
Contact Material & Plating	Brass, Gold over Nickel		
Dielectric Type	PTFE	PTFE	
Body Material & Plating	Brass, Nickel	Brass, Nickel	
Coupling Nut Material & Plating	Brass, Nickel	Brass, Nickel	

Environmental Specifications

Temperature

Operating Range

-55 to +125 deg C


Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:



Example: FMCA3055-12 = 12 inches long cable FMCA3055-100cm = 100 cm long cable

N Male to RA N Male Cable Tinned Copper RG405 Type .086 Coax in 150 CM Length from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: N Male to RA N Male Cable Tinned Copper RG405 Type .086 Coax in 150 CM Length FMCA3055-150CM

URL: https://www.fairviewmicrowave.com/n-male-to-ra-n-male-cable-rg405-type-.086-coax-fmca3055-150cm-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





