

30 dB WR-22 Waveguide Broadwall Coupler with UG-383/U Flange and 33 GHz to 50 GHz in Brass



FMW22CP006-30

Features

- · Three Port broadwall Waveguide Coupler
- 30±1 dB Nominal Coupling Level

Applications

- · Test Benches
- Radar
- Satellite
- · Microwave Radio

- 33 GHz to 50 GHz Frequency Range
- Low VSWR < 1.15:1
- · Attenuation Measurements
- Power Measurements
- · Source Leveling

Description

The FMW22CP006-30 is a 30 dB WR-22 three port broadwall coupler. This coupler can be mounted directly into the waveguide signal path, connected via coax to allow signal sampling /monitoring. The coupler has a typical VSWR of 1.15:1 and are made of Brass with UG-383/U flanges. The FMW22CP006-30 is part of a family of cross guide couplers offered by Fairview Microwave with coupling values ranging from 20 to 50 dB.

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	33		50	GHz
Coupler				
Nominal Coupling Level		30		dB
Coupling Accuracy		±1		dB
Directivity	30			dB
Insertion Loss			0.4	dB
Main Line VSWR			1.15:1	
Secondary Line VSWR			1.25:1	
Input Power (CW)			150	Watts
Input Power, Peak			10	kWatts

Mechanical Specifications

Size

 Length
 4.57 in [116.08 mm]

 Width
 1.74 in [44.2 mm]

 Height
 1.13 in [28.7 mm]

 Weight
 1 lbs [453.59 g]

Interface

Waveguide Size WR-22 Flange Type UG-383/U

Flange Material and Plating Brass Copper, Gold Coupler Body Material and Plating Brass Copper, Gold



30 dB WR-22 Waveguide Broadwall Coupler with UG-383/U Flange and 33 GHz to 50 GHz in Brass



FMW22CP006-30

Environmental Specifications

Temperature

Operating Range -40 to +70 deg C Storage Range -55 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

30 dB WR-22 Waveguide Broadwall Coupler with UG-383/U Flange and 33 GHz to 50 GHz in Brass from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 30 dB WR-22 Waveguide Broadwall Coupler with UG-383/U Flange and 33 GHz to 50 GHz in Brass FMW22CP006-30

URL: https://www.fairviewmicrowave.com/30db-wr22-waveguide-broadwall-coupler-ug-383-u-50ghz-fmw22cp006-30-p. aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

