



RA SMP Female Connector Solder Attachment For .047 SR Cable Up To 8 GHz

RA SMP female connector with solder attachment for .047 SR, part number SC5183, from Fairview Microwave is in-stock and ships same day. This SMP female connector operates up to a maximum frequency of 8 GHz and offers excellent VSWR of 1.1:1. This blind mate connector is ideal for applications without direct visual or tactile access to the connection point, for example, when two circuit boards need to be mated. Its right angle body geometry facilitates connections in tight spaces.

Fairview's RA SMP female connector SC5183 datasheet specifications and outline drawing are shown in this PDF below. Our extensive offering of RF, microwave and millimeter wave connectors allows designers to configure and customize their signal connections however they like. From providing an I/O for a board design to creating a custom cable assembly configuration, Fairview Microwave has a connector solution to meet your needs. Fairview Microwave also has the expertise to build your custom cable assemblies for you and ship them same-day.

Electrical Specifications

Description	Min	Тур	Max	Units
Frequency Range	DC	7.	8	GHz
	DC			GHZ
VSWR			1.1:1	
Operating Voltage (AC)			335	Vrms
DWV (AC)			500	Vrms
Inner Cond. DC Resistance	е		6	mOhms
Outer Cond. DC Resistance	е		2	mOhms
Insulation Resistance	5,000			MOhms



Configuration:

- SMP Female Connector
- MIL-STD-348A
- 50 Ohms
- Right Angle Body Geometry
- .047 SR Interface Type
- Solder Attachment

Features:

- Operating Frequency of 8 GHz Max.
- Excellent VSWR of 1.1:1
- Blind Mate Connector
- Gold Plated Beryllium Copper Contact

Applications:

- General Purpose Test
- Custom Cable Assemblies

Mechanical Specifications

Size

Length 0.28 in [7.11 mm] Width/Dia. 0.187 in [4.75 mm] 0.002 lbs [0.91 g] Weight

Material Specifications

Description	Material	Plating		
Contact	Beryllium Copper	Gold		
Insulation	PTFE			
Outer Conductor	Beryllium Copper	Gold		

Mechanical Specification Notes:

Minimum mating cycles: 100 (full detent), 500 (limited detent), 1,000

(smooth bore).

Environmental Specifications Temperature

Operating Range

-65 to +165 deg C

Fairview Microwave 1130 Junction Dr. #100 Allen, TX 75013

Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Humidity MIL-STD-202, Method 106 (except 7b omitted)
Shock MIL-STD-202, Method 213, Condition I
Vibration MIL-STD-202, Method 204, Condition D
Salt Spray MIL-STD-202, Method 101, Condition B

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

RA SMP Female Connector Solder Attachment For .047 SR Cable Up To 8 GHz from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: RA SMP Female Connector Solder Attachment For .047 SR Cable Up To 8 GHz SC5183


URL: https://www.fairviewmicrowave.com/smp-female-standard-.047-sr-connector-sc5183-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2016 REV 1.1 Page 2 of 3





- 1. STRIP CABLE AS SHOWN. DO NOT NICK CENTER CONDUCTOR.
- 2. SOLDER CONTACT TO CENTER CONDUCTOR.
- 3. INSERT CABLE INTO BODY UNTIL IT BOTTOMS OUT. SOLDER OUTER CONDUCTOR TO BODY.

FAIRVIEW MICROWAVE INC. ALLEN, TX 75013 WWW.FAIRVIEWMICROWAVE.COM	NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].					
RA SMP Female Connector Solder Attachment For .047	DWG NO SC5183			CAGE CODE 3FKR5		
SR Cable Up To 8 GHz	CAD FILE 082014	SHEET	SCAL	E N/A	SIZE A	2233