

## FMAD1610 DATA SHEET

# Engineering Grade 2.92mm Female (Jack) to 2.92mm Female (Jack) Adapter with Stainless Steel Body

2.92mm female to 2.92mm female adapter part number FMAD1610 from Fairview Microwave is in-stock and ships same day. This Fairview 2.92mm to 2.92mm adapter has a female to female gender configuration and is built of durable stainless steel in a engineering grade design. FMAD1610 2.92mm female to 2.92mm female adapter operates to 40 GHz. The 2.92mm connector mates mechanically with commercially available SMA and 3.5mm connectors.

RF adapters can be used to enable connections between two connector types that would otherwise not mate. Certain RF adapter configurations can also be used to protect connectors on expensive equipment where the number of connect and disconnect cycles is high. An RF, microwave, or millimeter wave adapter is connected to the equipment and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Fairview Microwave also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

### **Electrical Specifications**

Description	Min	Тур	Max	Units
Frequency Range	DC		40	GHz
VSWR		1.25:1		
DWV (AC)			750	Vrms
Insulation Resistance	5,000			MOhms

## **Specifications by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency Range	DC to 2	2 to 8	8 to 10	10 to 20	20 to 40	GHz
Insertion Loss, Max	0.071	0.141	0.158	0.224	0.316	dB

Electrical Specification Notes: Values at sea level

values at sea level

#### **Mechanical Specifications**

_			
-	ı	7	
_		_	_

Length	0.82 in [20.90 mm]
Width	0.31 in [7.90 mm]
Height	0.31 in [7.90 mm]
Weight	0.01 lbs [4.54 g]

Description	Connector 1	Connector 2
Туре	2.92mm Female	2.92mm Female
Polarity	Standard	Standard
Mating Cycles, Min	500	
Contact Captivation Axial Force, Min	4.9 lbs [2.22 kg]	4.9 lbs [2.22 kg]
Coupling Proof Torque	15 in-lbs [1.7 Nm]	15 in-lbs [1.7 Nm]



## **Configuration:**

- 2.92mm Female Connector 1
- 2.92mm Female Connector 2
- 50 Ohm
- Engineering Grade Design
- Straight Body Geometry

#### **Features:**

- Gold Plated Beryllium Copper Contact
- Max VSWR of 1.25:1 up to 40 GHz

## **Applications:**

• General Purpose Test

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





#### **Material Specifications**

Description	Connector 1	Connector 2	
Туре	2.92mm Female	2.92mm Female	
Contact Material	Beryllium Copper	Beryllium Copper	
Contact Plating	Gold	Gold	
Insulation Material	PPO	PPO	
Outer Contact Material	Beryllium Copper	Beryllium Copper	
Outer Contact Plating	Gold	Gold	
Body Material	Stainless Steel	Stainless Steel	
Body Plating	Passivated Stainless Steel	Passivated Stainless Steel	

#### **Environmental Specifications**

**Temperature** 

Operating Range -55 to +105 deg C Humidity MIL-STD-202, Method 206

Thermal Shock MIL-STD-202, Method 107, Condition B Salt Spray MIL-STD-202, Method 101, Condition B

**Compliance Certifications** (see product page for current document)

#### **Plotted and Other Data**

Notes:

Engineering Grade 2.92mm Female (Jack) to 2.92mm Female (Jack) Adapter with Stainless Steel Body from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: Engineering Grade 2.92mm Female (Jack) to 2.92mm Female (Jack) Adapter with Stainless Steel Body FMAD1610

URL: https://www.fairviewmicrowave.com/2-92mm-female-to-2-92mm-female-adapter-mil-std-202-method-206-stain-less-steel-engineering-grade-fmad1610-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2020 REV 1.0 Page 2 of 3





