

SMC Plug to MMCX Jack Cable RG-316 Coax




FMC00324


Configuration

Connector 1: SMC Plug
Connector 2: MMCX Jack
Cable Type: RG316
Coax Flex Type: Flexible

Features

- Max Frequency 3 GHz69% Phase Velocity
- FEP Jacket





Applications

· General Purpose

· Laboratory Use

Description

The SMC plug to MMCX jack cable using RG-316 coax, part number FMC00324, from Fairview Microwave is in-stock and ships same day. This Fairview SMC to MMCX cable assembly has a plug to jack gender configuration with 50 ohm flexible RG316 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00324 SMC plug to MMCX jack cable assembly operates to 3 GHz.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		3	GHz
VSWR			1.4:1	
Velocity of Propagation		69		%
Capacitance		29.4 [96.46]		pF/ft [pF/m]
Operating Voltage (AC)			250	Vrms
Jacket Spark			2,000	Vrms

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.1	0.25	0.5	1	3	GHz



SMC Plug to MMCX Jack Cable RG-316 Coax



FMC00324

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Insertion Loss (Typ.)	0.1	0.15	0.23	0.37	0.57	dB/ft
	0.33	0.49	0.75	1.21	1.87	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as 0.1 dB per connector.

Mechanical Specifications

Cable Assembly

Width/Diameter 0.5 in [12.7 mm]

Cable

Cable TypeRG316Impedance50 OhmsInner Conductor TypeStranded

Inner Conductor Material and Plating Copper Clad Steel, Silver

Dielectric Type PTFE
Number of Shields 1

Shield Layer 1 Silver Plated Copper Braid

Jacket Material FEP, Tan

Jacket Diameter 0.102 in [2.59 mm]

Connectors

Description	Connector 1	Connector 2	
Туре	SMC Plug	MMCX Jack	
Specification	MIL-STD-348A	BS EN 122340	
Impedance	50 Ohms	50 Ohms	
Configuration	Straight	Straight	
Contact Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold	
Contact Plating Specification	50 μin minimum	30 μin minimum	
Dielectric Type	PTFE	PTFE	
Body Material and Plating	Brass, Gold	Brass, Gold	
Body Plating Specification	3 μin minimum	3 µin minimum	
Coupling Nut Material and Plating	Brass, Gold		
Coupling Nut Plating Specification	3 μin minimum		
Hex Size	1/4 inch		

Environmental Specifications

Operating Range Temperature -55 to +200 deg C



SMC Plug to MMCX Jack Cable RG-316 Coax



FMC00324

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Typical Performance Data

How to Order

Example: FMC00324-12 = 12 inches long cable

FMC00324-100cm = 100 cm long cable

SMC Plug to MMCX Jack Cable RG-316 Coax from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Lewisville, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: SMC Plug to MMCX Jack Cable RG-316 Coax FMC00324

URL: https://www.fairviewmicrowave.com/smc-plug-to-mmcx-jack-cable-rg-316-coax-fmc00324-p.aspx

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to impliment improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume liability arising out of the use of any part or document.

