



RA TNC Male to TNC Female Bulkhead Cable LMR-100 Coax

The RA TNC male to TNC female bulkhead cable using LMR-100 coax, part number FMC00336, from Fairview Microwave is in-stock and ships same day. This Fairview TNC to TNC cable assembly has a male to female gender configuration with 50 ohm flexible LMR-100A coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00336 TNC male to TNC female cable assembly operates to 5.8 GHz. The right angle TNC interface on the LMR-100A cable allows for easier connections in tight spaces. Our RF cable assembly with TNC bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	Units	
Frequency Range	DC			5.8	GHz	
Velocity of Propagation		(66		%	
RF Shielding	90				dB	
Group Delay		1.54	[5.05]		ns/ft [ns/ı	m]
Capacitance		30.8 [101.05]	pF/ft [pF/ı	m]
Inductance		0.077	7 [0.25]		uH/ft [uH/	m]
DC Resistance Inner Cor	nductor	81 [2	265.75]		Ω/1000ft [Ω/	/Km]
DC Resistance Outer Cor	nductor	9.5 [31.17]		Ω/1000ft [Ω/	/Km]
Jacket Spark				2,000	Vrms	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	5.8	GHz
Insertion Loss (Typ.)	0.12	0.17	0.24	0.4	0.64	dB/ft
	0.39	0.56	0.79	1.31	2.1	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

Mechanical Specifications

Cable Assembly

Diameter

0.68 in [17.27 mm]



Configuration:

- TNC Male Right Angle
- TNC Female Bulkhead
- LMR-100A

Features:

- Max Frequency 5.8 GHz
- Shielding Effectivity > 90 dB
- 66% Phase Velocity
- · Double Shielded
- PVC Jacket

Applications:

- General Purpose
- · Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Cable

Cable Type LMR-100A Impedance 50 Ohms Inner Conductor Type Solid

Inner Conductor Material and Plating Copper Clad Steel Dielectric Type PE

Dielectric Type Number of Shields

Shield Layer 1 Aluminum Tape
Shield Layer 2 Tinned Copper Braid
Jacket Material PVC, Black

2

acket Material PVC, Black

Jacket Diameter 0.11 in [2.79 mm]

One Time Minimum Bend Radius 0.25 in [6.35 mm]
Repeated Minimum Bend Radius 1 in [25.4 mm]

Bending Moment 0.1 lbs-ft [0.14 N-m]
Flat Plate Crush 10 lbs/in [0.18 Kg/mm]

Tensile Strength 15 lbs [6.8 Kg]

Connectors

Description	Connector 1		Connector 2
Туре	TNC Ma	le	TNC Female
Mount Method			Bulkhead
Specification			MIL-STD-348
Impedance	50 Ohms		50 Ohms
Contact Material & Plating	Brass, Gold		Phosphor Bronze, Gold
Dielectric Type	Delrin		PTFE
Outer Cond Material & Plat	ing		Brass, Nickel
Body Material & Plating	Brass, Nic	ckel	Brass, Nickel
Coupling Nut Material & Pla	ating Brass, Nic	ckel	
Hex Size			5/8 in

Mechanical Specification Notes:

Environmental Specifications

Temperature

Operating Range -40 to +85 deg C Storage Range -70 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689

Copyright © 2019 REV 1.0 Page 2 of 4

^{*}All cable assemblies have a length tolerance of 1.5% or \pm 3/8", whichever is greater.





How to Order

Part Number Configuration:	FMC00336	- xx	uu	
				— cm = Centimeters <black> = Inches</black>
				— Length

Example: FMC00336-12 = 12 inches long cable

FMC00336-100cm = 100 cm long cable

RA TNC Male to TNC Female Bulkhead Cable LMR-100 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: RA TNC Male to TNC Female Bulkhead Cable LMR-100 Coax FMC00336

URL: https://www.fairviewmicrowave.com/ra-tnc-male-tnc-female-cable-lmr100-coax-fmc00336-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





