



Low Loss SMA Male to SMA Male Cable LMR-400-UF Coax With Times Microwave Components

The SMA male to SMA male cable using LMR-400-UF coax, part number FMCA1144, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to SMA cable assembly has a male to male gender configuration with 50 ohm flexible LMR-400-UF coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA1144 SMA male to SMA male cable assembly operates to 6 GHz. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Тур		Max l		Jnits	
Frequency Range	DC			6	(GHz	
VSWR				1.4:1			
Velocity of Propagation		8	85			%	
RF Shielding	90					dB	
Group Delay		1.2	[3.94]		ns/ft	[ns/n	n]
Capacitance		23.9	[78.41]		pF/ft	[pF/n	n]
Inductance	0.06 [0.2]			uH/ft [uH/m]			
DC Resistance Inner Cor	1.07	1.07 [3.51]			Ω/1000ft [Ω/Km]		
DC Resistance Outer Cor	1.65	[5.41]		Ω/1000	Oft [Ω/I	Km]	
Dielectric Withstanding Voltage (DC)				500	1	√dc	
Jacket Spark				8,000	V	rms	

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	6	GHz
Insertion Loss (Typ.)	0.02	0.03	0.05	0.08	0.13	dB/ft
	0.07	0.1	0.16	0.26	0.43	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of the connectors. Insertion Loss is estimated as $0.1\ dB$ per connector.

Mechanical Specifications

Cable Assembly

Weight 0.19 lbs [86.18 q]

Cable

Cable Type Impedance Inner Conductor Type LMR-400-UF 50 Ohms Stranded



Configuration:

- SMA Male
- SMA Male
- LMR-400-UF

Features:

- Max Frequency 6 GHz
- Shielding Effectivity > 90 dB
- 85% Phase Velocity
- Double Shielded
- TPE Jacket

Applications:

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com

sales@fairviewmicrowave.com





Inner Conductor Material and Plating

Dielectric Type Number of Shields

Shield Layer 1 Shield Layer 2 Jacket Material

Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius Bending Moment

Flat Plate Crush Tensile Strength Copper PE (F) 2

Aluminum Tape Tinned Copper Braid

TPE, Black

0.405 in [10.29 mm]

1 in [25.4 mm] 4 in [101.6 mm]

-40 to +85 deg C

0.38 lbs-ft [0.52 N-m] 20 lbs/in [0.36 Kg/mm] 160 lbs [72.57 Kg]

Connectors

Description	Connector 1	Connector 2				
Туре	SMA Male	SMA Male				
Impedance	50 Ohms	50 Ohms				
Contact Material & Plating	Brass, Gold	Brass, Gold				
Contact Plating Spec.	50μ" Min	50μ" Minimum				
Dielectric Type	Teflon	Teflon				
Body Material & Plating	Brass, Tri-Metal	Brass, Tri-Metal				
Coupling Nut Material & Pla	ting Brass, Tri-Metal	Brass, Tri-Metal				

Environmental Specifications

Temperature

Operating Range

Humidity MIL-STD-202, Method 106

Shock MIL-STD-202, Method 213, Condition I Vibration MIL-STD-202, Method 204, Condition B

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

How to Order

Part Number Configuration:

Example: FMCA1144-12 = 12 inches long cable

FMCA1144-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





Low Loss SMA Male to SMA Male Cable LMR-400-UF Coax With Times Microwave Components from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: Low Loss SMA Male to SMA Male Cable LMR-400-UF Coax With Times Microwave Components FMCA1144

URL: https://www.fairviewmicrowave.com/low-loss-sma-male-to-sma-male-cable-lmr-400-uf-coax-with-times-microwave-components-fmca1144-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order

											ulleu. Ollie		
stated, all	specification	ons are	nominal.	Fairvie	w Microwa	ve does n	ot make	any rep	resentat	ion or	warranty re	egard	ling the
suitability	of the part	describ	ed hereir	n for any	particular	purpose,	and Fair	view M	icrowave	does	not assume	any	liability
arising ou	t of the use	of any	part or do	ocument	ation.								

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





