

FMCA2738-24 DATA SHEET

SMA Male Right Angle to TNC Male Right Angle Cable in 24 Inch Length Using RG223 Coax

The RA SMA male to RA TNC male cable using RG223 coax, part number FMCA2738-24, from Fairview Microwave is in-stock and ships same day. This Fairview SMA to TNC cable assembly has a male to male gender configuration with 50 ohm flexible RG223 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA2738-24 SMA male to TNC male cable assembly operates to 3 GHz. The right angle SMA and right angle TNC interfaces on the RG223 cable allow for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	Units
Frequency Range	DC			3	GHz
Velocity of Propagation		6	66		%
Capacitance	30.8 [101.05]			pF/ft [pF/m]	
Operating Voltage (AC)				500	Vrms

Performance by Frequency

3 GHz
3 GHZ
0.8 dB/ft
2.62 dB/m
_

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax cable and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1 dB for the straight connector and 0.2 dB for the right angle connector.

Mechanical Specifications

Cable Assembly

Length* 24 in [609.6 mm] Weight 0.152 lbs [68.95 g]

Cable

Cable Type RG223
Impedance 50 Ohms
Inner Conductor Type Solid
Inner Conductor Material and Plating
Dielectric Type PE
Number of Shields 2



Configuration:

- SMA Male Right Angle
- TNC Male Right Angle
- RG223

Features:

- Max Frequency 3 GHz
- 66% Phase Velocity
- Double Shielded
- PVC Jacket

Applications:

- General Purpose
- · Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com

sales@fairviewmicrowave.com





Shield Layer 1 Shield Layer 2 Jacket Material Jacket Diameter Silver Plated Copper Braid Silver Plated Copper Braid

PVC, Black

0.21 in [5.33 mm]

One Time Minimum Bend Radius

1 in [25.4 mm]

Connectors

Description	Connector 1	Connector 2		
Туре	SMA Male	TNC Male		
Specification	MIL-STD-348A	MIL-STD-348A		
Impedance	50 Ohms	50 Ohms		
Contact Material & Plating	Brass, Gold	Brass, Gold		
Contact Plating Spec.	50µ in. minimum	30µ in. minimum		
Dielectric Type	Teflon	Teflon		
Body Material & Plating	Brass, Nickel	Brass, Nickel		
Body Plating Spec.	100µ in. minimum	100µ in. minimum		
Coupling Nut Material & Pla	Brass, Nickel			
Coupling Nut Plating Spec.		100µ in. minimum		
Hex Size	5/16 in			
Torque	5 in-lbs 0.57 Nm	5 in-lbs 0.57 Nm		

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Values at 25°C, sea level.

How to Order

Part Number Configuration:

FMCA2738 - xx uu | cm = Centimeters | chlank > = Inches | Length

Example: FMCA2738-12 = 12 inches long cable

FMCA2738-100cm = 100 cm long cable





SMA Male Right Angle to TNC Male Right Angle Cable in 24 Inch Length Using RG223 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: SMA Male Right Angle to TNC Male Right Angle Cable in 24 Inch Length Using RG223 Coax FMCA2738-24

URL: https://www.fairviewmicrowave.com/ra-sma-male-to-ra-tnc-male-cable-rg223-coax-in-24-inch-and-rohs-fmca2738-24-p.aspx







