

FMCA2764-48 DATA SHEET

TNC Male Right Angle to TNC Male Right Angle Cable in 48 Inch Length Using RG223 Coax

The RA TNC male to RA TNC male cable using RG223 coax, part number FMCA2764-48, from Fairview Microwave is in-stock and ships same day. This Fairview TNC to TNC cable assembly has a male to male gender configuration with 50 ohm flexible RG223 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMCA2764-48 TNC male to TNC male cable assembly operates to 3 GHz. The right angle TNC interfaces on the RG223 cable allow for easier connections in tight spaces. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

Description	Min	Т	ур	Max	Units
Frequency Range	DC			3	GHz
Velocity of Propagation		6	66		%
Capacitance		30.8 [101.05]	pF/ft [pF/m]
Operating Voltage (AC)				500	Vrms

Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.1	0.25	0.5	1	3	GHz
Insertion Loss (Typ.)	0.56	0.65	0.76	0.94	1.4	dB/ft
	1.84	2.13	2.49	3.08	4.59	dB/m

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.2 dB per connector.

Mechanical Specifications

Cable Assembly

Length* 48 in [121.92 cm]
Weight 0.269 lbs [122.02 g]

Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1

RG223 50 Ohms Solid

Copper, Silver

PE 2

Silver Plated Copper Braid



Configuration:

- TNC Male Right Angle
- TNC Male Right Angle
- RG223

Features:

- Max Frequency 3 GHz
- 66% Phase Velocity
- Double Shielded
- PVC Jacket

Applications:

- General Purpose
- · Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689

www.fairviewmicrowave.com sales@fairviewmicrowave.com





Shield Layer 2 Jacket Material Jacket Diameter Silver Plated Copper Braid PVC, Black

0.21 in [5.33 mm]

One Time Minimum Bend Radius

1 in [25.4 mm]

Connectors

Connector 1	Connector 2			
TNC Male	TNC Male			
MIL-STD-348A	MIL-STD-348A			
50 Ohms	50 Ohms			
Brass, Gold	Brass, Gold			
30µ in. minimum	30µ in. minimum			
Teflon	Teflon			
Brass, Nickel	Brass, Nickel			
100µ in. minimum	100µ in. minimum			
ting Brass, Nickel	Brass, Nickel			
100µ in. minimum	100µ in. minimum			
	TNC Male MIL-STD-348A 50 Ohms Brass, Gold 30µ in. minimum Teflon Brass, Nickel 100µ in. minimum			

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

• Values at 25°C, sea level.

How to Order

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





TNC Male Right Angle to TNC Male Right Angle Cable in 48 Inch Length Using RG223 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: TNC Male Right Angle to TNC Male Right Angle Cable in 48 Inch Length Using RG223 Coax FMCA2764-48

URL: https://www.fairviewmicrowave.com/ra-tnc-male-to-ra-tnc-male-cable-rg223-coax-in-48-inch-and-rohs-fmca2764-48-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order

to implem	ent improvements.	Fairview Micro	wave reserv	es the right	to make	such c	hanges a	as requir	ed. Unles	s otl	nerwise
stated, al	l specifications are n	ominal. Fairv	ew Microwa	ve does no	t make a	ny rep	resentati	on or wa	arranty re	gard	ing the
	of the part describe			purpose,	and Fairvi	iew Mi	crowave	does no	t assume	any	liability
arising ou	t of the use of any pa	art or docume	ntation.								





