

FMCA2775-60 DATA SHEET

N Female Bulkhead to TNC Female Cable in 60 Inch Length Using RG223 Coax

The type N female bulkhead to TNC female cable using RG223 coax, part number FMCA2775-60, from Fairview Microwave is in-stock and ships same day. This Fairview type N to TNC cable assembly has a female to female gender configuration with 50 ohm flexible RG223 coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. Our RF cable assembly with type N bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications. The double shielding of this Fairview cable assembly provides excellent shielding effectiveness.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.



Configuration:

- N Female Bulkhead
- TNC Female
- RG223

Features:

- 66% Phase Velocity
- Double Shielded
- PVC Jacket

Applications:

- General Purpose
- Laboratory Use

Electrical Specifications

| Description | Min | Тур | Max | Units |
|-------------------------|-----|-------------|-----|--------------|
| Velocity of Propagation | | 66 | | % |
| Capacitance | 3 | 30.8 [101.0 | 5] | pF/ft [pF/m] |

Mechanical Specifications

Cable Assembly

Length* 60 in [152.4 cm]
Weight 0.247 lbs [112.04 g]

Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1

RG223
50 Ohms
Solid
Copper, Silver
PE
Silver Plated Copper Braid

Shield Layer 2 Silver Plated Copper Braid Jacket Material PVC, Black Jacket Diameter 0.21 in [5.33 mm]

One Time Minimum Bend Radius 1 in [25.4 mm]

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678

Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Connectors

| Description | Connector 1 | Connector 2 | |
|----------------------------|------------------|---------------|--|
| Туре | N Female | TNC Female | |
| Mount Method | Bulkhead | | |
| Specification | MIL-STD-348A | | |
| Impedance | 50 Ohms | 50 Ohms | |
| Contact Material & Plating | Brass, Gold | | |
| Contact Plating Spec. | 30µ in. minimum | | |
| Dielectric Type | Teflon | | |
| Body Material & Plating | Brass, Nickel | Brass, Nickel | |
| Body Plating Spec. | 100µ in. minimum | | |
| | | | |

Compliance Certifications (see product page for current document)


Plotted and Other Data

Notes:

· Values at 25°C, sea level.

How to Order

Part Number Configuration:



Example: FMCA2775-12 = 12 inches long cable

FMCA2775-100cm = 100 cm long cable

N Female Bulkhead to TNC Female Cable in 60 Inch Length Using RG223 Coax from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: N Female Bulkhead to TNC Female Cable in 60 Inch Length Using RG223 Coax FMCA2775-60

URL: https://www.fairviewmicrowave.com/n-female-bulkhead-to-tnc-female-cable-rg223-coax-in-60-inch-and-rohs-fm-ca2775-60-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





